7 Electrical Parts List

❋ You can search for updated part codes through ITSELF web site.
URL : http://itself.sec.samsung.co.kr/

7-1-1 LE17IS Main PCB Parts

Level	Loc. No.	Code No.	Description	Specification	Remarks
0	LE17ISBB/EDC				
1	ST-LE17ISBB/EDC	-	1	SDI,HIGH-CON(DF-T)	-
3	BH94-00976C	-	ASSY PCB MAIN-ST	LE17IS	SNA
4	2306-000147	C414	C-FILM,LEAD-PPF	1uF,5%,250V,BK,26x24x15,22.5mm	SA
4	2306-000263	C452	C-FILM,LEAD-PPF	770nF,5%,250V,BK,26x21.5x13.5,	SA
4	2301-001195	C601	C-FILM,LEAD-PPF	150nF,10%,275VAC,BK,26x16.5x7,	SA
4	2301-001195	C602	C-FILM,LEAD-PPF	150nF,10%,275VAC,BK,26x16.5x7,	SA
4	2401-003619	C605	C-AL	270uF,20%,450V,GP,BK,25.4x50mm,10	SA
4	BH63-00134A	CIS1	SHIELD-BOTTOM	LE17KS,SECC,T1.0	SNA
4	BH63-00124A	CIS2	SHIELD-IC	LE17KS,SPTE,T0.2	SNA
4	BH63-00143A	CIS3	COVER-PCB R	LE17KS,ABS PC,IV16	SNA
4	BH63-00144A	CIS4	COVER-PCB L	LE17KS,ABS PC,IV16	SNA
4	BH68-00001A	CIS40	LABEL-MARK CDT	ART-PAPER100G,-,WHT,BLK,-,ALL,CDT	SNA
4	0204-002426	CIS6	FLUX	DF-201TVS,MIX,0.820,FLUX13%,14KG,-	SNA
4	0204-002420	CIS7	SOLVENT	1M-1000,C3H70H,96,-,-	SNA
4	3711-003895	CN201	CONNECTOR-HEADER	BOX,13P,1R,2mm,STRAIGHT,SN	SA
4	3711-003843	CN202	CONNECTOR-HEADER	BOX,8P,1R,2mm,STRAIGHT,SN	SA
4	3711-004484	CN203	CONNECTOR-HEADER	BOX,5P,1R,2mm,STRAIGHT,SN	SA
4	3711-000197	CN321	CONNECTOR-HEADER	1WALL,3P,1R,2.5mm,STRAIGHT,SN	SA
4	3711-005055	CN401	CONNECTOR-HEADER	1WALL,4P,1R,10MM/8.0MM,STRAIGHT,SN-PB,WHT	SA
4	3721-001053	CN601	PLUG-AC POWER	3P,-,-,NI	SNA
4	3301-000130	CORE_1	CORE-FERRITE	AC,23.5x9.4x12.6mm,1500,2800G	SNA
4	3301-001264	CORE_2	CORE-FERRITE	AC,18.2X9.7X28.2MM,1500,2800GAUSS	SNA
4	0402-001441	D403	DIODE-RECTIFIER	-,40V,3A,DO-201AD,BK	SA
4	0402-001295	D505	DIODE-RECTIFIER	GUR460L-5700,600V,4A,DO-201AD,BK	SA
4	0402-001295	D507	DIODE-RECTIFIER	GUR460L-5700,600V,4A,DO-201AD,BK	SA
4	0402-001227	D601	DIODE-BRIDGE	D3SBA60,600V,2.3A,SIP-4,BK	SA
4	0402-000005	D626	DIODE-RECTIFIER	31DF4,400V,3A,DO-201AD,BK	SA
4	6003-000122	FBT+H/S	SCREW-TAPTITE	BH,+,B,M4,L12,ZPC(YEL),SWRCH18	SNA
4	3601-001303	FH1	FUSE-RADIAL LEAD	250V,4A,TIME-LAG,CERAMIC,5X20MM	SA
4	6502-000127	HS601_CLAMP1	CABLE CLAMP	DAWH-18NB,ID15,-,NYLON66,NTR	SNA
4	6502-001058	HS601_CLMAP2	CABLE CLAMP	DAWH-50N,ID16.6,-,NYLON6/6,NTR	SNA
4	3704-001071	IC201_SOCKET	SOCKET-IC	42P,DIP,SN,1.778mm	SA
4	1204-002259	IC401	IC-DEF. PROCESSOR	STV9118,SDIP,32P,27.94x8.89mm,PLASTIC,13.2V,-,0to+70C,ST,IC-DEF. PROCESSOR	SNA
4	1203-003240	IC621	IC-POSI.FIXED REG.	L78M05,IPAK,3P,6.5x6.1mm,PLASTIC,4.75/5.25V,-,0to+150C,0.5A,-,ST	SA
4	1203-000165	IC622	IC-POSI.ADJUST REG.	78R12,TO-220,4P,-,PLASTIC,11.7/12.3V,1.5W,-20TO+80C,1A,-,ST	SA
4	BH27-00134A	L411	COIL CHOKE	100UH,CDTMO,100UH,10%,0.20HM,5.0A,AR8X25,60.5TS,18X40MM,11MM,USTC0.12X20,TR,-10C	SA
4	BH27-00150A	L441	COIL LINEARITY	HL-1527C,5.2uH,YL8115X27.5,11mm,18x17x55mm,15©™%6.5t°æ0.5t;22T/100DT,BK,20%,0.0	⚠ SNA
4	BH27-00061A	L601	COIL FILTER	-,33.0mH,0.1ohm,72Ts,28.*28,-,BK,SQE-2828,3A,-,-	SA
4	6003-001023	M/PCB+SH/BTM	SCREW-TAPTITE	RWH,+,B,M3,L10,ZPC(YEL),SWRCH1	SNA
4	0505-001689	Q401	FET-SILICON	IRFU210B,N,200V,2.7A,1.5OHM,2.5W,I-PAK	SA
4	0505-001689	Q561	FET-SILICON	IRFU210B,N,200V,2.7A,1.5OHM,2.5W,I-PAK	SA
4	2005-001163	R409	R-WIRE WOUND,NON	0.68ohm,1%,3W,AA,TP,5.5x15mm	SA
4	2003-000695	R414	R-METAL OXIDE(S)	430ohm,5%,3W,AA,TP,6x16mm	SA
4	3501-001111	RL601	RELAY-POWER	12VDC,250MW,5000MA,1FORMA,15MS,5MS	SA
4	6003-000133	SH/BTM+AC/SOCK	SCREW-TAPTITE	BH,+,S,M4,L8,ZPC(YEL),SWRCH18A,-	SNA
4	BH39-00453A	SIGNAL_CABLE	CBF SIGNAL	LE19IS,15P/06P,08P,20276-N1,1830mm,UL20276,BLACK,D-SUB/MALE,AWG28/30,30V,ATT. TY	SNA
4	BH26-00090B	T401	TRANS HORIZ.DRIVE	EI-1916,AN19J,7P,35.0MH,185TS/13TS/95TS,73.0UH,7.5/0.05OHM,PL3,EI-1916,170UH MAX	⚠ SA
4	BH26-00158A	T411	TRANS-H PULSE	EI-2820,AN19IS,10P,500uH,,,0.35uH,,,1.00/0.030,,PL3,DMR30,EI-2820,300uH,23*29.5*	SA
4	BH26-00084A	T501	TRANS FBT	FQM19A005,PS17N0,122UH,SM19C,FUR3757SU,113.2MOHM,80,14P,-10~+60,BK,27KV	⚠ SA
4	BH26-00086A	T561	TRANS-FOCUS	EE1916,5P,2.0MH MIN,290MH MIN,0.85OHM/32.0OHM,EE1916(PL3,SL-2),EE19*16,23.0UH MA	⚠ SA
4	BH26-00172B	T601	TRANS SWITCHING	EER3942,LE17IS,90~264V,PL3,PM2A,ER-3942,290uH,49uH	-
4	BH26-00163A	T602	TRANS	UU-1116,CU17K,5,18mH min,18mH min,2.7ohm MAX,10 ~ 55,FERRITE,UU-1116 SB-5S	SA
4	1404-001264	TH601	THERMISTOR-PTC	4.5OHM,+30/-20%,220V,290VAC,21A,-,TR	SA
4	1404-001020	TH602	THERMISTOR-NTC	8ohm,15%,-,17mW/C,BK	SA
4	BH96-00285B	HS490	ASSY HEAT SINK P	BH62-00055A,SPRING,J6920,DTV1500HFP,2SK2761,OIL SILICON	SNA
4	BH97-00505C	MICOM	ASSY MICOM	LE19IS	SA
5	0903-001194	IC201	IC-MICROCONTROLLER	3P863,8Bit,SDIP,42P,600MIL,12MHz,ST,CMOS,PLASTIC,5V,-,-40to+85C,1040BYTE,48KBYTE	SNA
5	BH82-00020J	CIS	A/S MICOM	LE19IS	SNA

Level	Loc. No.	CodeNo.	Description	Specification	Remarks
4	BH97-00508C	-	ASSY AUTO-(MAIN)ST	LE17IS	SNA
5	3301-000011	BD201	BEAD-AXIAL	,3.5x1.0x5.7mm,,BK,,,	SA
5	3301-000011	BD202	BEAD-AXIAL	,3.5x1.0x5.7mm,,BK,,,	SA
5	3301-000011	BD203	BEAD-AXIAL	,3.5x1.0x5.7mm,,BK,,,	SA
5	3301-000011	BD402	BEAD-AXIAL	,3.5x1.0x5.7mm,,BK,,,	SA
5	3301-000011	BD411	BEAD-AXIAL	,3.5x1.0x5.7mm,,BK,,,	SA
5	3301-000011	BD412	BEAD-AXIAL	,3.5x1.0x5.7mm,,BK,,,	SA
5	3301-000011	BD431	BEAD-AXIAL	,3.5x1.0x5.7mm,,BK,,,	SA
5	3301-000011	BD501	BEAD-AXIAL	,3.5x1.0x5.7mm,,BK,,,	SA
5	3301-001450	BD601	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	2201-000119	C201	C-CERAMIC,DISC	100NF,+80-20%,50V,Y5V,TP,8X3MM,5	SA
5	2401-000050	C202	C-AL	10uF,20%,16V,GP,TP,5x11,2.5	SA
5	2201-000389	C203	C-CERAMIC,DISC	0.022NF,5%,50V,C0G,TP,5X3MM,5	SA
5	2201-000389	C204	C-CERAMIC,DISC	0.022NF,5%,50V,C0G,TP,5X3MM,5	SA
5	2201-000144	C205	C-CERAMIC,DISC	0.1NF,5%,50V,C0G,TP,8.5X3MM,5	SA
5	2201-000017	C206	C-CERAMIC,DISC	1NF,10%,50V,Y5P,TP,5X3.5MM,5	SA
5	2201-000374	C207	C-CERAMIC,DISC	0.22NF,5%,50V,C0G,TP,10.5X3MM,5	SA
5	2401-000603	C208	C-AL	1UF,20%,50V,GP,TP,5X11,2	SA
5	2401-000603	C209	C-AL	1UF,20%,50V,GP,TP,5X11,2	SA
5	2401-000603	C210	C-AL	1UF,20%,50V,GP,TP,5X11,2	SA
5	2401-000603	C211	C-AL	1UF,20%,50V,GP,TP,5X11,2	SA
5	2201-000389	C212	C-CERAMIC,DISC	0.022NF,5%,50V,C0G,TP,5X3MM,5	SA
5	2401-002075	C260	C-AL	4.7uF,20%,50V,GP,TP,5x11,5	SA
5	2401-002463	C301	C-AL	470uF,20%,16V,GP,TP,8x11.5,5	SA
5	2301-000174	C302	C-FILM,LEAD-PEF	15nF,5%,100V,TP,7.2x4.0x7.5mm,	SA
5	2301-000148	C303	C-FILM,LEAD-PEF	10nF,5%,100V,TP,7x3.2x7mm,5mm	SA
5	2401-000852	C304	C-AL	220uF,20%,35V,GP,TP,8x11.5mm,5	SA
5	2305-000004	C305	C-FILM,LEAD-PEF	220nF,10%,100V,TP,12.7x16,5mm	SA
5	2301-000010	C306	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2401-002463	C307	C-AL	470uF,20%,16V,GP,TP,8x11.5,5	SA
5	2401-001914	C309	C-AL	1uF,20%,50V,BP,TP,5x11,5	SA
5	2301-000148	C310	C-FILM,LEAD-PEF	10nF,5%,100V,TP,7x3.2x7mm,5mm	SA
5	2301-000188	C312	C-FILM,LEAD-PEF	1nF,5%,100V,TP,10.5x12.5x6.5,5	SA
5	2201-000119	C321	C-CERAMIC,DISC	100NF,+80-20%,50V,Y5V,TP,8X3MM,5	SA
5	2401-000025	C322	C-AL	100uF,20%,16V,GP,TP,6.3x11,5	SA
5	2301-000168	C331	C-FILM,LEAD-PEF	150nF,5%,100V,TP,11.5x19mm,7.5	SA
5	2305-000237	C332	C-FILM,LEAD-PEF	1uF,5%,63V,TP,7.5x15.5mm,5mm	SA
5	2401-000031	C333	C-AL	47uF,20%,16V,GP,TP,5x11,5	SA
5	2401-000050	C401	C-AL	10uF,20%,16V,GP,TP,5x11,2.5	SA
5	2401-001218	C402	C-AL	4.7uF,20%,100V,WT,TP,5x11,5	SA
5	2301-000010	C403	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2301-000020	C404	C-FILM,LEAD-PEF	27nF,5%,100V,TP,7.3x4x12.5mm,5	SA
5	2301-001441	C405	C-FILM,LEAD-PPF	2nF,3%,1.6kV,TP,20x2.5x11mm,7.5	⚠ SA
5	2309-000106	C406	C-FILM,LEAD-OTHER	2.2nF,5%,1.6KV,TP,23x16x9,7.5m	⚠ SA
5	2401-003826	C411	C-AL	220UF,20%,63V,LR,TP,10X25MM,5	SA
5	2201-000285	C412	C-CERAMIC,DISC	1NF,10%,1KV,Y5P,TP,8X5MM,5	SA
5	2201-000012	C413	C-CERAMIC,DISC	0.22NF,10%,1KV,Y5P,TP,6.3X5MM,5	SA
5	2201-000003	C415	C-CERAMIC,DISC	0.068NF,10%,2KV,SL,TP,7X5MM,5	SA
5	2201-000732	C417	C-CERAMIC,DISC	0.68NF,10%,1KV,Y5P,TP,7X4MM,5	SA
5	2401-002463	C431	C-AL	470uF,20%,16V,GP,TP,8x11.5,5	SA
5	2305-000665	C432	C-FILM,LEAD-PEF	100nF,5%,63V,TP,7.5x4.0x5.0mm,	SA
5	2301-000148	C433	C-FILM,LEAD-PEF	10nF,5%,100V,TP,7x3.2x7mm,5mm	SA
5	2202-000573	C434	C-CERAMIC,MLC-RADIAL	0.82NF,5%,50V,C0G,TP,5.1X3.2X5.1MM,5	SA
5	2301-000020	C435	C-FILM,LEAD-PEF	27nF,5%,100V,TP,7.3x4x12.5mm,5	SA
5	2401-002075	C436	C-AL	4.7uF,20%,50V,GP,TP,5x11,5	SA
5	2401-000603	C437	C-AL	1UF,20%,50V,GP,TP,5X11,2	SA
5	2401-000031	C438	C-AL	47uF,20%,16V,GP,TP,5x11,5	SA
5	2301-000188	C439	C-FILM,LEAD-PEF	1nF,5%,100V,TP,10.5x12.5x6.5,5	SA
5	2301-000004	C440	C-FILM,LEAD-PEF	2.2nF,5%,100V,TP,5.5X10X2.9,5m	SA
5	2301-000106	C441	C-FILM,LEAD-PEF	1.5nF,0.05,100V,TP,10.5*12.5*6	SA
5	2301-000016	C442	C-FILM,LEAD-PEF	22nF,5%,100V,TP,7.2x4.5x9.0mm,	SA
5	2301-000168	C443	C-FILM,LEAD-PEF	150nF,5%,100V,TP,11.5x19mm,7.5	SA
5	2301-000188	C444	C-FILM,LEAD-PEF	1nF,5%,100V,TP,10.5x12.5x6.5,5	SA
5	2301-001249	C451	C-FILM,LEAD-PPF	68nF,5%,400V,TP,19x7x15mm,7.5	SA
5	2306-000197	C453	C-FILM,LEAD-PPF	390nF,5%,250V,TP,20*19*12,7.5m	SA
5	2306-000131	C454	C-FILM,LEAD-PPF	150nF,5%,250V,TP,19x16x7.5,7.5	SA
5	2301-001249	C455	C-FILM,LEAD-PPF	68nF,5%,400V,TP,19x7x15mm,7.5	SA
5	2301-001067	C456	C-FILM,LEAD-PPF	82nF,5%,400V,TP,19x15.5x7,7.5	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	2301-001249	C457	C-FILM,LEAD-PPF	68nF,5%,400V,TP,19x7x15mm,7.5	SA
5	2201-000291	C458	C-CERAMIC,DISC	1NF,10%,500V,Y5P,TP,7.5X3.5MM,5	SA
5	2401-000603	C459	C-AL	1UF,20%,50V,GP,TP,5X11,2	SA
5	2202-000654	C460	C-CERAMIC,MLC-RADIAL	100nF,10%,50V,X7R,TP,5.1x6.6x3.2mm,5	SA
5	2301-000294	C501	C-FILM,LEAD-PEF	56nF,5%,100V,TP,9.5x12.5mm,5mm	SA
5	2301-000013	C502	C-FILM,LEAD-PEF	4.7nF,5%,100V,TP,10.5x12.5x6.5	SA
5	2301-000312	C503	C-FILM,LEAD-PEF	8.2nF,5%,100V,TP,6x12.5mm,5mm	SA
5	2401-000025	C504	C-AL	100uF,20%,16V,GP,TP,6.3x11,5	SA
5	2201-000163	C505	C-CERAMIC,DISC	10NF,+80-20%,50V,Y5V,TP,7X3MM,2.5	SA
5	2305-000237	C506	C-FILM,LEAD-PEF	1uF,5%,63V,TP,7.5x15.5mm,5mm	SA
5	2202-000654	C507	C-CERAMIC,MLC-RADIAL	100nF,10%,50V,X7R,TP,5.1x6.6x3.2mm,5	SA
5	2401-000025	C508	C-AL	100uF,20%,16V,GP,TP,6.3x11,5	SA
5	2401-000025	C509	C-AL	100uF,20%,16V,GP,TP,6.3x11,5	SA
5	2305-000412	C510	C-FILM,LEAD-PEF	470nF,5%,63V,TP,-,5mm	SA
5	2303-000102	C511	C-FILM,LEAD-PEF	1.2nF,5%,1.6KV,TP,23*16*7.5,7.	SA
5	2201-000012	C512	C-CERAMIC,DISC	0.22NF,10%,1KV,Y5P,TP,6.3X5MM,5	SA
5	2401-000058	C513	C-AL	220uF,20%,100V,GP,TP,12.5x25,5	SA
5	2401-000031	C521	C-AL	47uF,20%,16V,GP,TP,5x11,5	SA
5	2202-002009	C530	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2401-000638	C531	C-AL	2.2uF,20%,350V,WT,TP,10x12.5mm	SA
5	2401-001576	C532	C-AL	47uF,20%,50V,GP,TP,8x11.5,5	SA
5	2401-002267	C533	C-AL	2.2uF,20%,250V,GP,TP,8x11.5,5	SA
5	2301-000213	C534	C-FILM,LEAD-PEF	220nF,5%,250V,TP,21.5x11,7.5	SA
5	2301-001480	C535	C-FILM,LEAD-PEF	2000NF,5%,100V,TP,17X16.5X9.5,7.5	SA
5	2401-001026	C536	C-AL	3.3UF,20%,50V,GP,TP,5X11,5	SA
5	2401-002300	C537	C-AL	47uF,20%,50V,GP,TP,6.3x11,5	SA
5	2305-000428	C541	C-FILM,LEAD-PEF	47nF,5%,250V,TP,11x9x4.5,5mm	SA
5	2401-000480	C551	C-AL	10uF,20%,50V,GP,TP,5x11,5	SA
5	2201-000129	C552	C-CERAMIC,DISC	0.1NF,10%,1KV,Y5P,TP,7X4MM,5	SA
5	2201-000285	C561	C-CERAMIC,DISC	1NF,10%,1KV,Y5P,TP,8X5MM,5	SA
5	2201-000285	C562	C-CERAMIC,DISC	1NF,10%,1KV,Y5P,TP,8X5MM,5	SA
5	2306-001011	C563	C-FILM,LEAD-PPF	56nF,5%,250V,TP,19x7.5x14.5,7.	SA
5	2301-000016	C564	C-FILM,LEAD-PEF	22nF,5%,100V,TP,7.2x4.5x9.0mm,	SA
5	2301-000174	C565	C-FILM,LEAD-PEF	15nF,5%,100V,TP,7.2x4.0x7.5mm,	SA
5	2201-000023	C603	C-CERAMIC,DISC	2.2NF,20%,250V,Y5U,TP,11X7MM,5	SA
5	2201-000023	C604	C-CERAMIC,DISC	2.2NF,20%,250V,Y5U,TP,11X7MM,5	SA
5	2401-000970	C606	C-AL	22uF,20%,50V,WT,TP,5x11,5	SA
5	2202-002009	C607	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2201-000325	C608	C-CERAMIC,DISC	2.2NF,10%,500V,Y5P,TP,9.5X4MM,5	SA
5	2201-000129	C609	C-CERAMIC,DISC	0.1NF,10%,1KV,Y5P,TP,7X4MM,5	SA
5	2201-000017	C610	C-CERAMIC,DISC	1NF,10%,50V,Y5P,TP,5X3.5MM,5	SA
5	2401-000611	C611	C-AL	1uF,20%,50V,WT,TP,5x11,5	SA
5	2305-000149	C613	C-FILM,LEAD-PEF	100nF,5%,100V,TP,12x12.5x6.5,5	SA
5	2301-000284	C614	C-FILM,LEAD-PEF	47nF,5%,100V,TP,8.5x12.5mm,5mm	SA
5	2401-001585	C615	C-AL	47uF,20%,50V,WT,TP,8x11.5,5	SA
5	2202-002009	C616	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2201-000023	C617	C-CERAMIC,DISC	2.2NF,20%,250V,Y5U,TP,11X7MM,5	SA
5	2401-000015	C618	C-AL	33uF,20%,50V,WT,-,6.3x11mm,2.5	SA
5	2201-000291	C619	C-CERAMIC,DISC	1NF,10%,500V,Y5P,TP,7.5X3.5MM,5	SA
5	2305-000178	C621	C-FILM,LEAD-PEF	10nF,5%,100V,TP,-,5mm	SA
5	2401-000039	C622	C-AL	1000uF,20%,16V,GP,TP,10x16,5	SA
5	2401-000025	C623	C-AL	100uF,20%,16V,GP,TP,6.3x11,5	SA
5	2401-000010	C624	C-AL	220uF,20%,16V,GP,-,6.3x11mm,2.	SA
5	2401-000010	C625	C-AL	220uF,20%,16V,GP,-,6.3x11mm,2.	SA
5	2401-000010	C626	C-AL	220uF,20%,16V,GP,-,6.3x11mm,2.	SA
5	2401-000039	C627	C-AL	1000uF,20%,16V,GP,TP,10x16,5	SA
5	2401-000058	C628	C-AL	220uF,20%,100V,GP,TP,12.5x25,5	SA
5	2401-003826	C629	C-AL	220UF,20%,63V,LR,TP,10X25MM,5	SA
5	2201-000732	C630	C-CERAMIC,DISC	0.68NF,10%,1KV,Y5P,TP,7X4MM,5	SA
5	2401-000039	C631	C-AL	1000uF,20%,16V,GP,TP,10x16,5	SA
5	2401-000058	C633	C-AL	220uF,20%,100V,GP,TP,12.5x25,5	SA
5	2201-000017	C634	C-CERAMIC,DISC	1NF,10%,50V,Y5P,TP,5X3.5MM,5	SA
5	0203-001600	CIS10	TAPE-PAPER	#53128,0.15,5.5,2000M,BEIGE	SNA
5	0203-001599	CIS9	TAPE-KRAFT	#53110,0.1,6,2000M,BRN	SNA
5	BH71-40300A	CN420	PIN-HINGE	BRASS,D2.36!,HEAT/SINK,SN	SNA
5	BH71-40300A	CN421	PIN-HINGE	BRASS,D2.36!,HEAT/SINK,SN	SNA
5	3711-000217	CN602	CONNECTOR-HEADER	1WALL,2P,1R,7.92MM,STRAIGHT,SN,NTR	SA
5	0401-000005	D201	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D251	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	0401-000005	D252	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0402-000274	D301	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0401-000005	D401	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D402	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0402-001118	D411	DIODE-RECTIFIER	UF1G,400V,1.2A,DO-204AC,TP	SA
5	0402-000274	D412	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0401-000004	D441	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0402-000274	D451	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0401-000005	D501	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D502	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D504	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D506	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D508	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D509	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0402-000274	D510	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0402-000012	D531	DIODE-RECTIFIER	UF4007,1KV,1A,DO-41,TP	SA
5	0402-000274	D532	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0402-000017	D533	DIODE-RECTIFIER	RGP02-12,1.2KV,0.5A,DO-204AL,TP	SA
5	0401-000005	D541	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0402-001114	D542	DIODE-RECTIFIER	1N4936GP,400V,1A,DO-201AD,TP	SA
5	0402-000546	D543	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41,TP	SA
5	0401-000005	D544	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D551	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0402-000012	D603	DIODE-RECTIFIER	UF4007,1KV,1A,DO-41,TP	SA
5	0402-000012	D604	DIODE-RECTIFIER	UF4007,1KV,1A,DO-41,TP	SA
5	0402-000546	D605	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41,TP	SA
5	0402-000546	D606	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41,TP	SA
5	0401-000005	D607	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D608	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D621	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0402-001194	D622	DIODE-RECTIFIER	UG2D,200V,2A,-,TP	SA
5	0402-000274	D623	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0402-000274	D624	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0402-001194	D627	DIODE-RECTIFIER	UG2D,200V,2A,-,TP	SA
5	0402-001118	D628	DIODE-RECTIFIER	UF1G,400V,1.2A,DO-204AC,TP	SA
5	6042-000001	EY301	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY302	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY401	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY402	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY403	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY404	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY405	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY411	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY415	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY422	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY423	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY454	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY455	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY501	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY502	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY503	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY504	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY505	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY506	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY507	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY601	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY602	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY603	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY604	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY605	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY606	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY607	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY608	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY621	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY622	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY623	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	BH71-40300A	GT401	PIN-HINGE	BRASS,D2.36!,HEAT/SINK,SN	SNA
5	BH71-40300A	GT402	PIN-HINGE	BRASS,D2.36!,HEAT/SINK,SN	SNA
5	BH71-40300A	GT601	PIN-HINGE	BRASS,D2.36!,HEAT/SINK,SN	SNA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	BH71-40300A	GT602	PIN-HINGE	BRASS,D2.36!,HEAT/SINK,SN	SNA
5	1103-001150	IC241	IC-EEPROM	24C081,1Kx8,DIP,8P,9.2x6.4mm,2.7/5.5V,-25to+70C	SA
5	1203-000610	IC501	IC-PWM CONTROLLER	494,DIP,16P,300MIL,PLASTIC,40V,1W,0TO+70C,250MA,4.75/5.25V,ST	SA
5	BH39-40305U	JP_DHH	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP1	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP10	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP11	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP12	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP13	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP14	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP15	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP16	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP17	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP18	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP19	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP20	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP21	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP22	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP23	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP24	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP25	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP26	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP27	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP28	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP29	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP3	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP30	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP31	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP32	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP33	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP34	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP35	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP36	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP37	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP38	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP39	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP4	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP40	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP41	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP42	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP43	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP44	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP45	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP46	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP47	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP48	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP49	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP5	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP50	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP51	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP52	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP53	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP54	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP57	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP58	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP60	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP61	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP62	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP63	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP64	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP65	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP66	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP67	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP68	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP69	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP7	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP70	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP71	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP72	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	BH39-40305U	JP73	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP74	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP75	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP76	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP77	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP78	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP79	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP8	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP80	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP82	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP83	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP9	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	2701-000189	L218	INDUCTOR-AXIAL	0.47UH,10%,2534	SA
5	2701-000116	L501	INDUCTOR-AXIAL	10UH,10%,4298	SA
5	BH41-00270A	MP1.0	PCB MAIN	LE19IS,FR-1,1,1.0,1.6T,247*247,LE19,MAIN	SNA
5	0501-000122	Q321	TR-SMALL SIGNAL	2N3904,NPN,625mW,TO-92,TP,100-300	SA
5	0501-000581	Q322	TR-SMALL SIGNAL	2N3906,PNP,625mW,TO-92,TP,100-300	SA
5	0501-000586	Q323	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000586	Q403	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000303	Q404	TR-SMALL SIGNAL	KSA733,PNP,250mW,TO-92,TP,120-240	SA
5	0501-000586	Q411	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000303	Q412	TR-SMALL SIGNAL	KSA733,PNP,250mW,TO-92,TP,120-240	SA
5	0501-000586	Q455	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000586	Q456	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000586	Q457	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000586	Q458	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000404	Q459	TR-SMALL SIGNAL	KSD1616-Y,NPN,750mW,TO-92,TP,135-270	SA
5	0501-000122	Q502	TR-SMALL SIGNAL	2N3904,NPN,625mW,TO-92,TP,100-300	SA
5	0501-000581	Q503	TR-SMALL SIGNAL	2N3906,PNP,625mW,TO-92,TP,100-300	SA
5	0501-000122	Q523	TR-SMALL SIGNAL	2N3904,NPN,625mW,TO-92,TP,100-300	SA
5	0501-000586	Q541	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000143	Q542	TR-SMALL SIGNAL	2N6520,PNP,625mW,TO-92,TP,30-200	SA
5	0501-000413	Q551	TR-SMALL SIGNAL	KSP44,NPN,625mW,TO-92,TP,50-200	SA
5	0501-000122	Q601	TR-SMALL SIGNAL	2N3904,NPN,625mW,TO-92,TP,100-300	SA
5	0501-000404	Q604	TR-SMALL SIGNAL	KSD1616-Y,NPN,750mW,TO-92,TP,135-270	SA
5	0501-000010	Q621	TR-SMALL SIGNAL	KSC1008,NPN,800mW,TO-92,TP,120-240	SA
5	0501-000586	Q622	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000586	Q624	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000321	Q625	TR-SMALL SIGNAL	KSB1116-Y,PNP,750mW,TO-92,TP,135-270	SA
5	2001-000429	R201	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R202	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R203	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R204	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R205	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R206	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000800	R207	R-CARBON	5.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000739	R208	R-CARBON	4.7MOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R209	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R210	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R211	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R212	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R213	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R214	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R215	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000006	R216	R-CARBON	2.4KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000006	R217	R-CARBON	2.4KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000793	R218	R-CARBON	47OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R219	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R220	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R221	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R222	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R223	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R224	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R227	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000435	R228	R-CARBON	1MOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000435	R229	R-CARBON	1MOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R230	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000554	R231	R-CARBON	270OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000869	R232	R-CARBON	56OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	2001-000869	R233	R-CARBON	56OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R234	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R235	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R236	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R241	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R242	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R243	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R244	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000977	R301	R-CARBON	8.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2004-000216	R302	R-METAL	10Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2004-000616	R304	R-METAL	24Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2001-001078	R305	R-CARBON(S)	15KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2004-001005	R306	R-METAL	5.1Kohm,1%,1/4W,AA,TP,2.4x6.4m	SA
5	2004-004038	R307	R-METAL	4.3Kohm,1%,1/4W,AA,TP,2.4x6.4m	SA
5	2004-004231	R308	R-METAL(S)	2.4OHM,1%,1/2W,AA,TP,3.3X9MM	SA
5	2004-001391	R309	R-METAL(S)	2.2ohm,1%,1/2W,AA,TP,2.4x6.4mm	SA
5	2001-000037	R310	R-CARBON(S)	330OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000290	R311	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001053	R312	R-CARBON(S)	1.5OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000977	R313	R-CARBON	8.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R321	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000331	R322	R-CARBON	12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000302	R323	R-CARBON	10OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000864	R324	R-CARBON	56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000042	R325	R-CARBON	1KOHM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000281	R326	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001079	R327	R-CARBON(S)	15OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-001079	R328	R-CARBON(S)	15OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000319	R401	R-CARBON	120KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000221	R402	R-CARBON	1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000221	R403	R-CARBON	1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000490	R404	R-CARBON	200OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000739	R405	R-CARBON	4.7MOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000052	R406	R-CARBON(S)	3.3KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-001078	R407	R-CARBON(S)	15KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2003-000505	R408	R-METAL OXIDE(S)	150ohm,5%,3W,AA,TP,6x16mm	SA
5	2003-000763	R410	R-METAL OXIDE(S)	6.8ohm,5%,3W,AA,TP,6x16mm	SA
5	2003-000468	R411	R-METAL OXIDE(S)	10ohm,5%,1W,AA,TP,3.3x9mm	SA
5	2001-000008	R412	R-CARBON	15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2003-000005	R413	R-METAL OXIDE(S)	1ohm,5%,2W,AA,TP,4x12mm	SA
5	2001-000107	R415	R-CARBON(S)	150KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2004-001118	R431	R-METAL	5Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2001-000449	R432	R-CARBON	2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2004-004367	R433	R-METAL	90Kohm,1%,1/4W,AA,TP,6.2x2.6mm	SA
5	2001-000449	R434	R-CARBON	2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000010	R435	R-CARBON	68KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000356	R436	R-CARBON	150KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2004-001230	R437	R-METAL	75Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2004-000657	R438	R-METAL	27Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2004-000412	R439	R-METAL	18Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2001-000890	R440	R-CARBON	6.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000577	R441	R-CARBON	2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000009	R442	R-CARBON	20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R451	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R452	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R453	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R454	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000411	R455	R-CARBON	18KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000411	R456	R-CARBON	18KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000411	R457	R-CARBON	18KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000411	R458	R-CARBON	18KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R459	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R460	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R461	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R462	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2003-000450	R463	R-METAL OXIDE(S)	100Kohm,5%,3W,AA,TP,6x16mm	SA
5	2003-000541	R464	R-METAL OXIDE(S)	1Kohm,5%,3W,AA,TP,6x16mm	SA
5	2003-000671	R465	R-METAL OXIDE(S)	390ohm,5%,2W,AA,TP,4x12mm	SA
5	2001-000290	R467	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	2003-000514	R468	R-METAL OXIDE(S)	15ohm,5%,2W,AA,TP,4x12mm	SA
5	BH39-40305U	R469	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	2001-000241	R501	R-CARBON	1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R502	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000812	R503	R-CARBON	5.6KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000689	R504	R-CARBON	390KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000786	R505	R-CARBON	47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R506	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000331	R507	R-CARBON	12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R509	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000241	R510	R-CARBON	1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001153	R511	R-CARBON(S)	47OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-001144	R512	R-CARBON(S)	4.7KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2005-001172	R513	R-WIRE WOUND,NON	0.6ohm,5%,3W,AA,TP,5.5x15mm	SA
5	2003-000432	R515	R-METAL OXIDE(S)	1.5Kohm,5%,3W,AA,TP,6x16mm	SA
5	2004-001005	R516	R-METAL	5.1Kohm,1%,1/4W,AA,TP,2.4x6.4m	⚠ SA
5	2001-000878	R520	R-CARBON	6.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000800	R521	R-CARBON	5.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2004-001136	R522	R-METAL	6.8Kohm,1%,1/4W,AA,TP,2.4x6.4m	SA
5	2001-000734	R523	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2004-001298	R526	R-METAL	82Kohm,2%,1/4W,AA,TP,2.4x6.4mm	⚠ SA
5	2001-000429	R530	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000073	R531	R-CARBON	33KOHM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2004-000781	R532	R-METAL	330Kohm,1%,1/4W,AA,TP,2.4x6.4m	⚠ SA
5	2004-000560	R533	R-METAL	220Kohm,1%,1/4W,AA,TP,2.4x6.4m	⚠ SA
5	2001-000800	R534	R-CARBON	5.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2004-000252	R535	R-METAL	11Kohm,1%,1/4W,AA,TP,2.4x6.4mm	⚠ SA
5	2001-000591	R541	R-CARBON	3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R542	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2002-001091	R543	R-COMPOSITION	270KOHM,5%,1/2W,AA,TP,3X9MM	SA
5	2002-001062	R544	R-COMPOSITION	150Kohm,2%,1/2W,AA,TP,3.9x9mm	SA
5	2002-000121	R545	R-COMPOSITION	1Mohm,10%,1/2W,AA,TP,3.5x9.5mm	SA
5	2001-000734	R550	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R551	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000331	R553	R-CARBON	12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R554	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R555	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2002-001079	R556	R-COMPOSITION	470Kohm,5%,1/2W,AA,TP,4x10mm	SA
5	2002-001079	R557	R-COMPOSITION	470Kohm,5%,1/2W,AA,TP,4x10mm	SA
5	2001-000114	R558	R-CARBON(S)	180KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000114	R559	R-CARBON(S)	180KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2003-000514	R561	R-METAL OXIDE(S)	15ohm,5%,2W,AA,TP,4x12mm	SA
5	2001-000221	R562	R-CARBON	1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001129	R601	R-CARBON(S)	330KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-001129	R602	R-CARBON(S)	330KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2003-000738	R603	R-METAL OXIDE(S)	56Kohm,5%,2W,AA,TP,4x12mm	SA
5	2003-000014	R604	R-METAL OXIDE(S)	10Kohm,5%,3W,AA,TP,6x16mm	SA
5	2002-001103	R605	R-COMPOSITION	300Kohm,5%,1/2W,AA,TP,3.7x10.0mm	SA
5	2002-001103	R606	R-COMPOSITION	300Kohm,5%,1/2W,AA,TP,3.7x10.0mm	SA
5	2001-001116	R607	R-CARBON(S)	27OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000734	R608	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000780	R609	R-CARBON	470OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R610	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	BH39-40305U	R611	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	2001-000023	R621	R-CARBON	47OHM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000027	R622	R-CARBON	100OHM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000613	R623	R-CARBON	3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000857	R624	R-CARBON	560OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R626	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R627	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000472	R628	R-CARBON	2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000786	R629	R-CARBON	47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2003-000473	R631	R-METAL OXIDE(S)	10ohm,5%,3W,AA,TP,6x16mm	SA
5	2001-001108	R632	R-CARBON(S)	22KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000613	R634	R-CARBON	3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	4715-001055	SK531	SURGE ABSORBER	1kV,+50-10%,-,-,RADIAL	SNA
5	6042-000002	TP501	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	2801-000006	X201	CRYSTAL-UNIT	12MHz,50ppm,28-AAM,S,35ohm,BK	SA
5	0403-001327	ZD201	DIODE-ZENER	MTZJ18A,16.22-17.06V,500MW,DO-34,TP	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	0403-001068	ZD202	DIODE-ZENER	UZ4.7BSA,4.44-4.68V,500MW,DO-34,TP	SA
5	0403-000361	ZD221	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD222	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD223	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD224	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD225	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD501	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-001167	ZD541	DIODE-ZENER	MTZJ30D,29.02-30.51V,500MW,DO-34,TP	SA
5	BH39-40305U	ZD542	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	0403-001068	ZD543	DIODE-ZENER	UZ4.7BSA,4.44-4.68V,500MW,DO-34,TP	SA
5	0403-001221	ZD601	DIODE-ZENER	UZ39BSB,35.36-37.19V,500MW,DO-34,TP	SA
5	0403-000361	ZD602	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
4	BH99-00030F	HS422	ASSY HEAT/SINK	HS TR,SCREW+NUT,IRFS630B(4),OIL SILICON	SNA
5	0205-001154	CIS	OIL-SILICON	G746,-,-	SNA
5	0505-001716	CIS	FET-SILICON	IRFS630B,N,200V,9A,0.4OHM,38W,TO-220F	SA
5	6006-001008	CIS	SCREW-ASS'Y MACH	WSP,BH,+,M3,L10,ZPC(YEL),SWRCH	SNA
5	6021-000118	CIS	NUT-HEXAGON	1C,M3,ZPC(YEL),SM20C	SNA
5	BH62-00044A	CIS	HEAT SINK-TR	AQ19FS,A1050S,T2.0,20,55,-,-,-	SNA
4	BH99-10019H	HS411	ASSY HEAT/SINK	H/S TR,SCREW+NUT,IRF634A,-,-,OIL SILICON,-,-	SNA
5	0205-001154	CIS	OIL-SILICON	G746,-,-	SNA
5	0505-001181	CIS	FET-SILICON	IRF634A,N,250V,8.1A,450mohm,74	SA
5	6006-001008	CIS	SCREW-ASS'Y MACH	WSP,BH,+,M3,L10,ZPC(YEL),SWRCH	SNA
5	6021-000118	CIS	NUT-HEXAGON	1C,M3,ZPC(YEL),SM20C	SNA
5	BH62-30024B	CIS	HEAT SINK-IC	SPC-1,T1,SN COATING,-	SNA
4	BP96-00065B	HS301	ASSY HEAT SINK P	BH62-00003B,SCREW,STV9325,OIL SILICON	SNA
5	0205-001154	H/S	OIL-SILICON	G746,-,-	SNA
5	1204-002262	H/S	IC-VERTICAL DEF.	STV9325,HEPTAWATT,7P,15.45x10.22mm,PLASTIC,35V,-,-40to+150C,ST,IC-VERTICAL DEF.	SNA
5	6003-000334	H/S	SCREW-TAPTITE	RH,+,2S,M3,L6,ZPC(YEL),SWRCH18	SNA
5	BH62-00003B	H/S	HEAT SINK-VERT	A1050S,T1.0,T1.0,-,DA,DB	SNA
4	BP96-00075D	HS601	ASSY HEAT SINK P	BH62-00052A,SPRING,8SA0965,SILICON RUBBER	SNA
5	BH13-00049A	H/S	IC HYBRID	FS8S0965RCB(DP906C),LE19IS,5,-25 to 85,TO-220(FORMING),35,ST	SA
5	BH61-00004A	H/S	SPRING ETC-TR	CDA,CDB,SUS304,-,-,-,-,-,T0.5,-,-,-	SNA
5	BH62-00052A	H/S	HEAT SINK-POWER	M782,A1050S,T1.0,W25,L55,-,BH62,-	SNA
5	BH62-20001B	H/S	TUBE-RUBBER	CSQ4357,W25*L20*T0.45,-,-,-,-	SNA

7-1-2 LE17IS Video PCB Parts

Level	Loc. No.	Code No.	Description	Specification	Remarks
3	BH94-00978A	-	ASSY PCB VIDEO-ST	LE19IS	SNA
4	6003-001023	-	SCREW-TAPTITE	RWH,+,B,M3,L10,ZPC(YEL),SWRCH1	SNA
4	BH39-00386A	CIS	CBF-GROUND ASS'Y	MS17J0,8*0.16*16TA,1P/2P,80MM,35750-1010,EARTH PLATE CLIP,BK,8*0.16*16TA	SA
4	BH63-00131A	CIS1	SHIELD-VIDEO	LE17KS,SPTE,T0.2	SNA
4	0204-002426	CIS3	FLUX	DF-201TVS,MIX,0.820,FLUX13%,14KG,-	SNA
4	0204-002420	CIS4	SOLVENT	1M-1000,C3H70H,96,-,-	SNA
4	BH68-00001A	CIS40	LABEL-MARK CDT	ART-PAPER100G,-,WHT,BLK,-,ALL,CDT	SNA
4	3711-004236	CN101	CONNECTOR-HEADER	BOX,6P,1R,2MM,STRAIGHT,SN	SNA
4	BH39-00015A	CN102	CBF-HARNESS	13P/14P,200MM,WHT/BLK/RED/BLU,UL1007,AWG26,SMH200-13/YBNH200-14	SA
4	BH13-00050A	IC102	IC HYBRID	NT6813K-30031,NT6813K-30031,24P,-55 to +150,240mA,-0.5 to 6V,ST	SA
4	3704-001203	SK101	SOCKET-CRT	9P,29PI,22.5PI,NI+SN,-	SNA
4	BH96-00283B	HS106	ASSY HEAT SINK P	BH62-00054A,SCREW,LM2463,OIL SILICON	SNA
5	0205-001154	H/S	OIL-SILICON	G746,-,-	SNA
5	1201-002116	H/S	IC-VIDEO AMP	LM2463,TO-220,11P,17.5x20.01mm,-,-20,PLASTIC,100V,-,0to70C,-,-,-,-,-,ST	SA
5	6003-000334	H/S	SCREW-TAPTITE	RH,+,2S,M3,L6,ZPC(YEL),SWRCH18	SNA
5	BH62-00054A	H/S	HEAT SINK-PS	LEO,A1050S,2.0,112,25	SNA
4	BH97-00510A	-	ASSY AUTO-(VIDEO)ST	LE19IS	SNA
5	3301-001450	BD101	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	3301-001450	BD102	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD104	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001660	BD105	BEAD-RADIAL	100OHM,3.5X9.0X0.8,50MA,TP,K-150,00HM	SA
5	3301-001450	BD106	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	2202-002009	C101	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2401-000025	C103	C-AL	100uF,20%,16V,GP,TP,6.3x11,5	SA
5	2401-000603	C104	C-AL	1UF,20%,50V,GP,TP,5X11,2	SA
5	2201-000019	C106	C-CERAMIC,DISC	10nF,+80-20%,500V,Y5V,TP,13.5x4mm,5	SA
5	2401-003036	C111	C-AL	100uF,20%,16V,GP,TP,5X11mm,5mm	SA
5	2202-002009	C112	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2401-003036	C113	C-AL	100uF,20%,16V,GP,TP,5X11mm,5mm	SA
5	2201-000119	C114	C-CERAMIC,DISC	100NF,+80-20%,50V,Y5V,TP,8X3MM,5	SA
5	2401-003036	C115	C-AL	100uF,20%,16V,GP,TP,5X11mm,5mm	SA
5	2202-002009	C116	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2301-000148	C117	C-FILM,LEAD-PEF	10nF,5%,100V,TP,7x3.2x7mm,5mm	SA
5	2201-000483	C118	C-CERAMIC,DISC	0.033NF,5%,50V,C0G,TP,5X3.5MM,5	SA
5	2401-003036	C119	C-AL	100uF,20%,16V,GP,TP,5X11mm,5mm	SA
5	2202-002009	C120	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2401-003036	C121	C-AL	100uF,20%,16V,GP,TP,5X11mm,5mm	SA
5	2202-002009	C122	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2301-000010	C123	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2401-000049	C124	C-AL	47uF,20%,100V,WT,TP,10x16,5	SA
5	2202-002009	C125	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2201-000119	C126	C-CERAMIC,DISC	100NF,+80-20%,50V,Y5V,TP,8X3MM,5	SA
5	2201-000119	C131	C-CERAMIC,DISC	100NF,+80-20%,50V,Y5V,TP,8X3MM,5	SA
5	2201-000019	C132	C-CERAMIC,DISC	10nF,+80-20%,500V,Y5V,TP,13.5x4mm,5	SA
5	2201-000154	C133	C-CERAMIC,DISC	10NF,+80-20%,2KV,Y5P,TP,20X5MM,7.5	SA
5	2202-000286	C134	C-CERAMIC,MLC-AXIAL	56pF,5%,50V,SL,TP,1.9x3.5,-	SA
5	2202-000286	C135	C-CERAMIC,MLC-AXIAL	56pF,5%,50V,SL,TP,1.9x3.5,-	SA
5	2202-002009	CB01	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2202-002009	CB02	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2301-000010	CB03	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2401-003911	CB04	C-AL	1uF,20%,160V,BP,TP,6.3x11mm,5	SA
5	2202-002009	CG01	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2202-002009	CG02	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2301-000010	CG03	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2401-003911	CG04	C-AL	1uF,20%,160V,BP,TP,6.3x11mm,5	SA
5	6502-000001	CIS	CABLE CLAMP	DAWH-5NB,D15,L35,NYLON66,NTR	SNA
5	0203-001599	CIS6	TAPE-KRAFT	#53110,0.1,6,2000M,BRN	SNA
5	0203-001600	CIS7	TAPE-PAPER	#53128,0.15,5.5,2000M,BEIGE	SNA
5	BH71-40300A	CN_G2	PIN-HINGE	BRASS,D2.36!,HEAT/SINK,SN	SNA
5	BH71-40300A	CN_GND	PIN-HINGE	BRASS,D2.36!,HEAT/SINK,SN	SNA
5	2202-002009	CR01	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2202-002009	CR02	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2301-000010	CR03	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2401-003911	CR04	C-AL	1uF,20%,160V,BP,TP,6.3x11mm,5	SA
5	0401-000005	DB01	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	DB02	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000004	DB03	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DB04	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DB05	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000005	DG01	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	DG02	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000004	DG03	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DG04	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DG05	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000005	DR01	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	DR02	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000004	DR03	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DR04	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DR05	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	6042-000001	EY1	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY2	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY3	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY4	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY5	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	BH13-00022A	IC104	IC HYBRID-BIAS CLAMP	LM2480NA,PN15H/17L,8P,0to+70C,DIP,3mA,85V,ST	SA
5	BH39-40305U	JP101	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP102	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	BH39-40305U	JP103	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP104	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP105	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	2701-001062	LB01	INDUCTOR-AXIAL	0.12UH,10%,3070	SA
5	2701-001092	LB02	INDUCTOR-AXIAL	0.07uH,10%,2360	SA
5	2701-001062	LG01	INDUCTOR-AXIAL	0.12UH,10%,3070	SA
5	2701-001092	LG02	INDUCTOR-AXIAL	0.07uH,10%,2360	SA
5	2701-001062	LR01	INDUCTOR-AXIAL	0.12UH,10%,3070	SA
5	2701-001092	LR02	INDUCTOR-AXIAL	0.07uH,10%,2360	SA
5	BH41-00271A	MP1.0	PCB-VIDEO	LE19IS,FR-1,1,1.0,1.6T,82.3*123.5,LE19,6,VIDEO	SNA
5	2001-000577	R102	R-CARBON	2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R103	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R105	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R106	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000016	R107	R-CARBON(S)	1OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000435	R111	R-CARBON	1MOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000812	R112	R-CARBON	5.6KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R113	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R114	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001138	R131	R-CARBON(S)	390OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000037	R132	R-CARBON(S)	330OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000947	R134	R-CARBON	7.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000084	R135	R-CARBON	100Kohm,5%,1/4W,AA,TP,2.4x6.4mm	SA
5	2001-000969	RB01	R-CARBON	75OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000969	RB02	R-CARBON	75OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	RB03	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001187	RB05	R-CARBON(S)	75OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000429	RB06	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001129	RB07	R-CARBON(S)	330KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000022	RB08	R-CARBON(S)	33OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000969	RG01	R-CARBON	75OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000969	RG02	R-CARBON	75OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	RG03	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001199	RG05	R-CARBON(S)	91OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000429	RG06	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001129	RG07	R-CARBON(S)	330KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000022	RG08	R-CARBON(S)	33OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000969	RR01	R-CARBON	75OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000969	RR02	R-CARBON	75OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	RR03	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001187	RR05	R-CARBON(S)	75OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000429	RR06	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001129	RR07	R-CARBON(S)	330KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000022	RR08	R-CARBON(S)	33OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	1405-001064	SK104	SURGE ABSORBER	400V,20%,-,-,AXIAL	SA
5	4715-001065	SK105	SURGE ABSORBER	200V,20%,-,-,RADIAL	SNA
5	4715-001055	SK108	SURGE ABSORBER	1kV,+50-10%,-,-,RADIAL	SNA
5	4715-001065	SKB01	SURGE ABSORBER	200V,20%,-,-,RADIAL	SNA
5	4715-000102	SKG01	SURGE ABSORBER	200V,20%,1000A,-,RADIAL	SNA
5	4715-000102	SKR01	SURGE ABSORBER	200V,20%,1000A,-,RADIAL	SNA
5	0403-001068	ZD105	DIODE-ZENER	UZ4.7BSA,4.44-4.68V,500MW,DO-34,TP	SA

7-1-3 LE17IS Others

Level	Loc. No.	Code No.	Description	Specification	Remarks
2	BH90-00592A	-	ASSY COVER REAR	LE17JS,EDC	SNA
3	BH63-00130A	C/R	COVER-REAR	LE17KS,ABS HB,IV16	SNA
2	BH90-00598A	-	ASSY STAND	LE17JS/LE15VS,EDC	SNA
3	BH96-00272A	STD	ASSY STAND P	LE17KS,ABS HB IV16	SNA
4	6902-000109	STD	BAG PE	HDPE,T0.015,L430,W350,TRP,28,2,PE MARK	SNA

Level	Loc. No.	Code No.	Description	Specification	Remarks
4	BH60-00030A	STD	FASTENER-BAND	PN17LT,ST+PVC,P0.4,-,150,YELLOW,-,-,-	SNA
4	BH61-00049A	STD	STAND-BASE	LE17KS,ABS HB,IV16	SNA
4	BH61-00050A	STD	STAND-TOP	LE17KS,ABS HB,IV16	SNA
4	BH61-40002A	STD	FOOT-RUBBER	-,NR,PMS428U,GA4237,-,-,-	SNA
4	BH63-30103A	STD	FELT-STAND	MCM1755,FELT,T1.0,W10,L4	SNA
4	BH68-20366A	STD	LABEL-MARK STAND	,ART PAPER100(S),WHT	SNA
4	BH68-70306A	STD	CARD-STAND	CVM4967PWS(SKD),WONSTROW,CHAIN	SNA
2	BH90-00611C	-	ASSY COVER FRONT	LE17IS	SNA
3	6003-000009	C/F+C/R	SCREW-TAPTITE	BH,+,B,M4,L16,ZPC(YEL),SWRCH18	SNA
3	6006-001119	C/F+CDT	SCREW-ASS'Y TAPT	WC,BH,+,M5,L25,ZPC(YEL),SWRCH18A	SNA
3	BH96-00274C	C/F	ASSY COVER P-FRONT	LE17IS,ABS HB IV16	SNA
4	6003-001023	C/F	SCREW-TAPTITE	RWH,+,B,M3,L10,ZPC(YEL),SWRCH1	SNA
4	BH63-00126A	C/F	COVER-FRONT	LE17KS,ABS HB,IV16,DF-SYNCMASTER	SNA
4	BH64-00151A	C/F	KNOB-FUNCTION	LE17KS,ABS,HB,IV16	SNA
4	BH67-00045A	C/F	LENS-LED	LE17KS,ACRYL,CLEAR,SYNCMASTER	SNA
4	BH72-00298A	C/F	GUIDE-CDT	,ABS,IV16,PN17LT,HB	SNA
4	BH72-60491B	C/F	CAP-BOSS	CGK5517,TPE,80,GRAY,CDT SETTING	SA
4	BH96-00287A	C/F	ASSY BOARD P-FUNCTION	LE19IS,FUNTION	SNA
4	BN68-00434A	C/F	LABEL-TC003	CDT,TC0'03,PE CLAER,T0.05,25*20,6DO SILK	SNA
2	BH91-00843Q	-	ASSY CDT-ST	LE19IS	SNA
3	0201-001576	CDT	ADHESIVE-RBR	DC-3140_RTV#0414,TRP,-,-	SNA
3	0203-000005	CDT	TAPE-ACETATE	SGT730,T0.26,W19,L3000,BLK	SNA
3	3302-000006	CDT	MAGNET-RUBBER	AF,14G,1620-1980G,0.58-0.9MGOe	SA
3	3309-000002	CDT	MAGNET-SHEET	5x20x80mm,UL94V-0,2	SA
3	BH03-00075C	CDT	CDT-ST	M41QCJ761X851(T4),84,17,0.25,29.1,IFT,H/C,NH,TCO,TILT,4	SA
3	BH68-30003C	CDT	LABEL-00,HIGH,VOLTAGE	SS,ART100G,30*33,YEL	SNA
3	BH96-00292A	CDT	ASSY D-COIL P	17 inch,BH27-00148A,BH96-00289A	SNA
2	BH91-00870A	-	ASSY SHIELD	LE17JS	SNA
3	0201-001059	CIS	ADHESIVE-SIL	#9590,WHT,-,CARTRIGE	SNA
3	6003-001023	SH/COV+SH/BTM	SCREW-TAPTITE	RWH,+,B,M3,L10,ZPC(YEL),SWRCH1	SNA
3	BH96-00281A	CIS	ASSY MISC P-SHIELD COVER	LE17KS,SECC T0.5,AL T0.25	SNA
4	BH63-00132A	CIS	SHIELD-COVER TOP	LE17KS,AL,T0.25	SNA
4	BH63-00133A	CIS	SHIELD-COVER REAR	LE17KS,SECC,T0.5	SNA
4	BH63-00145A	CIS	SHEET-ANODE	LE17KS,PP V2,T1.0,WHITE	SNA
2	BH91-00919D	-	ASSY CHASSIS-ST	LE17IS,EDC	SNA
2	BH92-01069A	-	ASSY P/MATERIAL	LE17JS	SNA
3	0203-001100	P/M	TAPE-OPP MASKING	OPP/W75/CLR,T0.05,W75,L800000,CLR	SNA
3	0203-001598	P/M	TAPE-FILAMENT	#8915,0.15,12,55000,CLR	SNA
3	6902-000001	P/M	BAG AIR	LDPE,T0.2,L1800,W1000,TRP,,,LDPE ONLY	SNA
3	6902-000379	P/M	BAG AIR	HDPE,T0.2,L1800,W1000,TRP,,,PAPER	SNA
3	6902-000523	P/M	BAG PE	HDPE,T0.015,W900,L800,TRP,28 LANGUAGE,2-	SNA
3	6902-000609	P/M	BAG ROLL	LDPE,T0.05,W2400,L1000,TRP,-,-	SNA
3	BH69-00561A	P/M	CUSHION	LE17KS,EPS M50,DF	SNA
3	BH69-40380A	P/M	PACKING-PAD	DW-2,500X2200X200,-,CGK5527	SNA
2	BH92-01093A	-	ASSY LABEL	LEO-PJT(15/17/19)	SNA
3	BH68-00565A	LABEL	LABEL RATING-00	ALL,SS,PE,T0.05,90*65,BLK,POLYESTER,NO SILK	SNA
2	BH92-01149E	-	ASSY BOX	LE17IS	SNA
3	BH68-00530A	BOX	LABEL BOX-01	LABEL-BARCODE,CE+TC003,MOJO 90G,WHT	SNA
3	BH69-00575A	BOX	BOX-00,MONITOR	S/M797DF(LE17IS) W/W,CB-SW4,YEL,A-1,W452*D506*H435	SNA
2	BH92-01162A	-	ASSY ACCESSORY	LEO	SNA
3	BH96-00297A	UNIT/ACCESSORY	ASSY ACCESSORY	LEO	SNA
4	0203-000214	ACCESSORY	TAPE-OPP MASKING	OPP/W50/CLR,T0.05,W50,L400000,	SNA
4	6902-000110	ACCESSORY	BAG PE	LDPE,T0.05,L356,W240,TRP,28,2,PE MARK	SNA
4	BH39-10339H	ACCESSORY	CBF POWER CORD	DET,H05VV-F,250V/10,16A,BLK,25	SA
4	BH68-70418A	ACCESSORY	CARD-EU BLOC WARR-07	SyncMaster,BASIC,EU,MOJO,100G,	SNA

Level	Loc. No.	Code No.	Description	Specification	Remarks
4	BH96-00296A	ACCESSORY	ASSY MANUAL P-IB+QSG	795DF,SyncMaster,W/W,27Lang,BH59-362A+BH68-376J	SNA
5	BH59-00362A	I/B	S/W DRIVER-00,IB	793S,795DF,W/W,SYNCMASTER,27LANG	SNA
5	BH68-00376J	QUICK	MANUAL-01	AN_QUICK SETUP GUIDE,SYNCMASTER,E/F/S/G/P/I..14LANGS,W/W,MOJO100G,298,420	SNA

7-2-1 LE19IS Main PCB Parts

Level	Loc. No.	Code No.	Description	Specification	Remarks
0	LE19ISBB				
1	ST-LE19ISBB	-	1	SDI,HIGH-CON(DF-T)	-
3	BH94-00989L	-	ASSY PCB MAIN-SX	LEO	SNA
4	2306-000147	C414	C-FILM,LEAD-PPF	1uF,5%,250V,BK,26x24x15,22.5mm	SA
4	2306-000263	C452	C-FILM,LEAD-PPF	770nF,5%,250V,BK,26x21.5x13.5,	SA
4	2301-001195	C601	C-FILM,LEAD-PPF	150nF,10%,275VAC,BK,26x16.5x7,	SA
4	2301-001195	C602	C-FILM,LEAD-PPF	150nF,10%,275VAC,BK,26x16.5x7,	SA
4	2401-003483	C605	C-AL	270uF,20%,400V,GP,BK,25.4x45,10	SA
4	BH63-00134A	CIS1	SHIELD-BOTTOM	LE17KS,SECC,T1.0	SNA
4	BH63-00124A	CIS2	SHIELD-IC	LE17KS,SPTE,T0.2	SNA
4	BH63-00143A	CIS3	COVER-PCB R	LE17KS,ABS PC,IV16	SNA
4	BH63-00144A	CIS4	COVER-PCB L	LE17KS,ABS PC,IV16	SNA
4	BH68-00001A	CIS40	LABEL-MARK CDT	ART-PAPER100G,-,WHT,BLK,-,ALL,CDT	SNA
4	0204-002426	CIS6	FLUX	DF-201TVS,MIX,0.820,FLUX13%,14KG,-	SNA
4	0204-002420	CIS7	SOLVENT	1M-1000,C3H70H,96,-,-	SNA
4	3711-003895	CN201	CONNECTOR-HEADER	BOX,13P,1R,2mm,STRAIGHT,SN	SA
4	3711-003843	CN202	CONNECTOR-HEADER	BOX,8P,1R,2mm,STRAIGHT,SN	SA
4	3711-004484	CN203	CONNECTOR-HEADER	BOX,5P,1R,2mm,STRAIGHT,SN	SA
4	3711-000885	CN321	CONNECTOR-HEADER	3WALL,3P,1R,2.5mm,STRAIGHT,SN	SA
4	3711-005055	CN401	CONNECTOR-HEADER	1WALL,4P,1R,10MM/8.0MM,STRAIGHT,SN-PB,WHT	SA
4	3721-001053	CN601	PLUG-AC POWER	3P,-,-,NI	SNA
4	3301-000130	CORE_1	CORE-FERRITE	AC,23.5x9.4x12.6mm,1500,2800G	SNA
4	3301-001264	CORE_2	CORE-FERRITE	AC,18.2X9.7X28.2MM,1500,2800GAUSS	SNA
4	0402-001441	D403	DIODE-RECTIFIER	-,40V,3A,DO-201AD,BK	SA
4	0402-001295	D505	DIODE-RECTIFIER	GUR460L-5700,600V,4A,DO-201AD,BK	SA
4	0402-001295	D507	DIODE-RECTIFIER	GUR460L-5700,600V,4A,DO-201AD,BK	SA
4	0402-001227	D601	DIODE-BRIDGE	D3SBA60,600V,2.3A,SIP-4,BK	SA
4	0402-000005	D626	DIODE-RECTIFIER	31DF4,400V,3A,DO-201AD,BK	SA
4	6003-000122	FBT+H/S	SCREW-TAPTITE	BH,+,B,M4,L12,ZPC(YEL),SWRCH18	SNA
4	3601-001303	FH1	FUSE-RADIAL LEAD	250V,4A,TIME-LAG,CERAMIC,5X20MM	SA
4	6502-000127	HS601_CLAMP1	CABLE CLAMP	DAWH-18NB,ID15,-,NYLON66,NTR	SNA
4	6502-001058	HS601_CLMAP2	CABLE CLAMP	DAWH-50N,ID16.6,-,NYLON6/6,NTR	SNA
4	3704-001071	IC201_SOCKET	SOCKET-IC	42P,DIP,SN,1.778mm	SA
4	1204-002259	IC401	IC-DEF. PROCESSOR	STV9118,SDIP,32P,27.94x8.89mm,PLASTIC,13.2V,-,0to+70C,ST,IC-DEF. PROCESSOR	SNA
4	1203-003240	IC621	IC-POSI.FIXED REG.	L78M05,IPAK,3P,6.5x6.1mm,PLASTIC,4.75/5.25V,-,0to+150C,0.5A,-,ST	SA
4	1203-000165	IC622	IC-POSI.ADJUST REG.	78R12,TO-220,4P,-,PLASTIC,11.7/12.3V,1.5W,-20TO+80C,1A,-,ST	SA
4	BH27-00134A	L411	COIL CHOKE	100UH,CDTM0,100UH,10%,0.20HM,5.0A,AR8X25,60.5TS,18X40MM,11MM,USTC0.12X20,TR,-10C	SA
4	BH27-00150A	L441	COIL LINEARITY	HL-1527C,5.2uH,YL8115X27.5,11mm,18x17x55mm,15©™x6.5t°±0.5t,22T/1000T,BK,20%,0.0	⚠ SNA
4	BH27-00061A	L601	COIL FILTER	-,33.0mH,0.1ohm,72Ts,28.*28,-,BK,SQE-2828,3A,-,-	SA
4	6003-001023	M/PCB+SH/BTM	SCREW-TAPTITE	RWH,+,B,M3,L10,ZPC(YEL),SWRCH1	SNA
4	0505-001689	Q401	FET-SILICON	IRFU210B,N,200V,2.7A,1.5OHM,2.5W,I-PAK	SA
4	0505-001689	Q561	FET-SILICON	IRFU210B,N,200V,2.7A,1.5OHM,2.5W,I-PAK	SA
4	2005-001163	R409	R-WIRE WOUND,NON	0.68ohm,1%,3W,AA,TP,5.5x15mm	SA
4	2003-000695	R414	R-METAL OXIDE(S)	430ohm,5%,3W,AA,TP,6x16mm	SA
4	3501-001111	RL601	RELAY-POWER	12VDC,250MW,5000MA,1FORMA,15MS,5MS	SA
4	6003-000133	SH/BTM+AC/SOCK	SCREW-TAPTITE	BH,+,S,M4,L8,ZPC(YEL),SWRCH18A,-	SNA
4	BH39-00453A	SIGNAL_CABLE	CBF SIGNAL	LE19IS,15P/06P,08P,20276-N1,1830mm,UL20276,BLACK,D-SUB/MALE,AWG28/30,30V,ATT. TY	SNA
4	BH26-00090B	T401	TRANS HORIZ.DRIVE	EI-1916,AN19J,7P,35.0MH,185TS/13TS/95TS,73.0UH,7.5/0.050HM,PL3,EI-1916,170UH MAX	⚠ SA
4	BH26-00174A	T411	TRANS-H PULSE	ER-2828,LE19IS,10P,500uH,0.70uH,0.2/0.030,PL-,DMR30,ER-2828,230uH,BK	SNA
4	BH26-00084A	T501	TRANS FBT	FQM19A005,PS17N0,122UH,SM19C,FUR3757SU,113.2MOHM,80,14P,-10~+60,BK,27KV	⚠ SA
4	BH26-00086A	T561	TRANS-FOCUS	EE1916,5P,2.0MH MIN,290MH MIN,0.850HM/32.00HM,EE1916(PL3,SL-2),EE19*16,23.0UH MA	⚠ SA
4	BH26-00172A	T601	TRANS SWITCHING	LE19IS,90~264V,FERRITE,ER-3942	SNA
4	BH26-00163A	T602	TRANS	UU-1116,CU17K,5,18mH min,18mH min,2.7ohm MAX,10 ~ 55,FERRITE,UU-1116 SB-5S	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
4	1404-001264	TH601	THERMISTOR-PTC	4.5OHM,+30/-20%,220V,290VAC,21A,-,TR	SA
4	1404-001020	TH602	THERMISTOR-NTC	8ohm,15%,-,17mW/C,BK	SA
4	BH96-00285A	HS490	ASSY HEAT SINK P	BH62-00055A,SPRING,J6920,FFAF10U170S,2SK2761,OIL SILICON	SNA
5	0205-001154	H/S	OIL-SILICON	G746,-,-	SNA
5	0402-001520	H/S	DIODE-RECTIFIER	FFAF10U170S,1700V,10A,DO-201AD,ST	SA
5	0502-001259	H/S	TR-POWER	FJAF6920A,NPN,60000mW,TO-3PF,ST,6-9	SA
5	0505-001266	H/S	FET-SILICON	2SK2761-01MR,N,600V,10A,0.85oh	SA
5	BH61-70003A	H/S	SPRING ETC	CVT4857,STS304-W1/2H,W3.8,-,L30,L30,-,T0.5,DEGRE,W3.8,STS304-W1/2H	SNA
5	BH62-00055A	H/S	HEAT SINK-PS	NEO,A1050S,2.0,80,100	SNA
4	BH97-00505C	MICOM	ASSY MICOM	LE19IS	SA
5	0903-001194	IC201	IC-MICROCONTROLLER	3P863,8Bit,SDIP,42P,600MIL,12MHz,ST,CMOS,PLASTIC,5V,-,-40to+85C,1040BYTE,48KBYTE	SNA
5	BH82-00020J	CIS	A/S MICOM	LE19IS	SNA
4	BH97-00508A	-	ASSY AUTO-(MAIN)ST	LE19IS	SNA
5	3301-000011	BD201	BEAD-AXIAL	,3.5x1.0x5.7mm,,BK,,,	SA
5	3301-000011	BD202	BEAD-AXIAL	,3.5x1.0x5.7mm,,BK,,,	SA
5	3301-000011	BD203	BEAD-AXIAL	,3.5x1.0x5.7mm,,BK,,,	SA
5	3301-000011	BD402	BEAD-AXIAL	,3.5x1.0x5.7mm,,BK,,,	SA
5	3301-000011	BD411	BEAD-AXIAL	,3.5x1.0x5.7mm,,BK,,,	SA
5	3301-000011	BD412	BEAD-AXIAL	,3.5x1.0x5.7mm,,BK,,,	SA
5	3301-000011	BD431	BEAD-AXIAL	,3.5x1.0x5.7mm,,BK,,,	SA
5	3301-000011	BD501	BEAD-AXIAL	,3.5x1.0x5.7mm,,BK,,,	SA
5	3301-001450	BD601	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	2201-000119	C201	C-CERAMIC,DISC	100NF,+80-20%,50V,Y5V,TP,8X3MM,5	SA
5	2401-000050	C202	C-AL	10uF,20%,16V,GP,TP,5x11,2.5	SA
5	2201-000389	C203	C-CERAMIC,DISC	0.022NF,5%,50V,C0G,TP,5X3MM,5	SA
5	2201-000389	C204	C-CERAMIC,DISC	0.022NF,5%,50V,C0G,TP,5X3MM,5	SA
5	2201-000144	C205	C-CERAMIC,DISC	0.1NF,5%,50V,C0G,TP,8.5X3MM,5	SA
5	2201-000017	C206	C-CERAMIC,DISC	1NF,10%,50V,Y5P,TP,5X3.5MM,5	SA
5	2201-000374	C207	C-CERAMIC,DISC	0.22NF,5%,50V,C0G,TP,10.5X3MM,5	SA
5	2401-000603	C208	C-AL	1UF,20%,50V,GP,TP,5X11,2	SA
5	2401-000603	C209	C-AL	1UF,20%,50V,GP,TP,5X11,2	SA
5	2401-000603	C210	C-AL	1UF,20%,50V,GP,TP,5X11,2	SA
5	2401-000603	C211	C-AL	1UF,20%,50V,GP,TP,5X11,2	SA
5	2201-000389	C212	C-CERAMIC,DISC	0.022NF,5%,50V,C0G,TP,5X3MM,5	SA
5	2401-002075	C260	C-AL	4.7uF,20%,50V,GP,TP,5x11,5	SA
5	2401-002463	C301	C-AL	470uF,20%,16V,GP,TP,8x11.5,5	SA
5	2301-000174	C302	C-FILM,LEAD-PEF	15nF,5%,100V,TP,7.2x4.0x7.5mm,	SA
5	2301-000148	C303	C-FILM,LEAD-PEF	10nF,5%,100V,TP,7x3.2x7mm,5mm	SA
5	2401-000852	C304	C-AL	220uF,20%,35V,GP,TP,8x11.5mm,5	SA
5	2305-000004	C305	C-FILM,LEAD-PEF	220nF,10%,100V,TP,12.7x16,5mm	SA
5	2301-000010	C306	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2401-002463	C307	C-AL	470uF,20%,16V,GP,TP,8x11.5,5	SA
5	2401-001914	C309	C-AL	1uF,20%,50V,BP,TP,5x11,5	SA
5	2301-000148	C310	C-FILM,LEAD-PEF	10nF,5%,100V,TP,7x3.2x7mm,5mm	SA
5	2301-000188	C312	C-FILM,LEAD-PEF	1nF,5%,100V,TP,10.5x12.5x6.5,5	SA
5	2201-000119	C321	C-CERAMIC,DISC	100NF,+80-20%,50V,Y5V,TP,8X3MM,5	SA
5	2401-000025	C322	C-AL	100uF,20%,16V,GP,TP,6.3x11,5	SA
5	2301-000168	C331	C-FILM,LEAD-PEF	150nF,5%,100V,TP,11.5x19mm,7.5	SA
5	2305-000237	C332	C-FILM,LEAD-PEF	1uF,5%,63V,TP,7.5x15.5mm,5mm	SA
5	2401-000031	C333	C-AL	47uF,20%,16V,GP,TP,5x11,5	SA
5	2401-000050	C401	C-AL	10uF,20%,16V,GP,TP,5x11,2.5	SA
5	2401-001218	C402	C-AL	4.7uF,20%,100V,WT,TP,5x11,5	SA
5	2301-000010	C403	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2301-000020	C404	C-FILM,LEAD-PEF	27nF,5%,100V,TP,7.3x4x12.5mm,5	SA
5	2301-001441	C405	C-FILM,LEAD-PPF	2nF,3%,1.6kV,TP,20x2.5x11mm,7.5	⚠ SA
5	2309-000106	C406	C-FILM,LEAD-OTHER	2.2nF,5%,1.6KV,TP,23x16x9,7.5m	⚠ SA
5	2401-003826	C411	C-AL	220UF,20%,63V,LR,TP,10X25MM,5	SA
5	2201-000285	C412	C-CERAMIC,DISC	1NF,10%,1KV,Y5P,TP,8X5MM,5	SA
5	2201-000012	C413	C-CERAMIC,DISC	0.22NF,10%,1KV,Y5P,TP,6.3X5MM,5	SA
5	2201-000003	C415	C-CERAMIC,DISC	0.068NF,10%,2KV,SL,TP,7X5MM,5	SA
5	2201-000732	C417	C-CERAMIC,DISC	0.68NF,10%,1KV,Y5P,TP,7X4MM,5	SA
5	2401-002463	C431	C-AL	470uF,20%,16V,GP,TP,8x11.5,5	SA
5	2305-000665	C432	C-FILM,LEAD-PEF	100nF,5%,63V,TP,7.5x4.0x5.0mm,	SA
5	2301-000148	C433	C-FILM,LEAD-PEF	10nF,5%,100V,TP,7x3.2x7mm,5mm	SA
5	2202-000573	C434	C-CERAMIC,MLC-RADIAL	0.82NF,5%,50V,C0G,TP,5.1X3.2X5.1MM,5	SA
5	2301-000020	C435	C-FILM,LEAD-PEF	27nF,5%,100V,TP,7.3x4x12.5mm,5	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	2401-002075	C436	C-AL	4.7uF,20%,50V,GP,TP,5x11,5	SA
5	2401-000603	C437	C-AL	1UF,20%,50V,GP,TP,5X11,2	SA
5	2401-000031	C438	C-AL	47uF,20%,16V,GP,TP,5x11,5	SA
5	2301-000188	C439	C-FILM,LEAD-PEF	1nF,5%,100V,TP,10.5x12.5x6.5,5	SA
5	2301-000004	C440	C-FILM,LEAD-PEF	2.2nF,5%,100V,TP,5.5X10X2.9,5m	SA
5	2301-000106	C441	C-FILM,LEAD-PEF	1.5nF,0.05,100V,TP,10.5*12.5*6	SA
5	2301-000016	C442	C-FILM,LEAD-PEF	22nF,5%,100V,TP,7.2x4.5x9.0mm,	SA
5	2301-000168	C443	C-FILM,LEAD-PEF	150nF,5%,100V,TP,11.5x19mm,7.5	SA
5	2301-000188	C444	C-FILM,LEAD-PEF	1nF,5%,100V,TP,10.5x12.5x6.5,5	SA
5	2301-001249	C451	C-FILM,LEAD-PPF	68nF,5%,400V,TP,19x7x15mm,7.5	SA
5	2306-000006	C453	C-FILM,LEAD-PPF	330nF,5%,250V,TP,20x18.5x10.5,	SA
5	2306-000131	C454	C-FILM,LEAD-PPF	150nF,5%,250V,TP,19x16x7.5,7.5	SA
5	2301-001249	C455	C-FILM,LEAD-PPF	68nF,5%,400V,TP,19x7x15mm,7.5	SA
5	2301-001067	C456	C-FILM,LEAD-PPF	82nF,5%,400V,TP,19x15.5x7,7.5	SA
5	2301-001249	C457	C-FILM,LEAD-PPF	68nF,5%,400V,TP,19x7x15mm,7.5	SA
5	2201-000291	C458	C-CERAMIC,DISC	1NF,10%,500V,Y5P,TP,7.5X3.5MM,5	SA
5	2401-000603	C459	C-AL	1UF,20%,50V,GP,TP,5X11,2	SA
5	2202-000654	C460	C-CERAMIC,MLC-RADIAL	100nF,10%,50V,X7R,TP,5.1x6.6x3.2mm,5	SA
5	2301-000294	C501	C-FILM,LEAD-PEF	56nF,5%,100V,TP,9.5x12.5mm,5mm	SA
5	2301-000013	C502	C-FILM,LEAD-PEF	4.7nF,5%,100V,TP,10.5x12.5x6.5	SA
5	2301-000312	C503	C-FILM,LEAD-PEF	8.2nF,5%,100V,TP,6x12.5mm,5mm	SA
5	2401-000025	C504	C-AL	100uF,20%,16V,GP,TP,6.3x11,5	SA
5	2201-000163	C505	C-CERAMIC,DISC	10NF,+80-20%,50V,Y5V,TP,7X3MM,2.5	SA
5	2305-000237	C506	C-FILM,LEAD-PEF	1uF,5%,63V,TP,7.5x15.5mm,5mm	SA
5	2202-000654	C507	C-CERAMIC,MLC-RADIAL	100nF,10%,50V,X7R,TP,5.1x6.6x3.2mm,5	SA
5	2401-000025	C508	C-AL	100uF,20%,16V,GP,TP,6.3x11,5	SA
5	2401-000025	C509	C-AL	100uF,20%,16V,GP,TP,6.3x11,5	SA
5	2305-000412	C510	C-FILM,LEAD-PEF	470nF,5%,63V,TP,-,5mm	SA
5	2303-000102	C511	C-FILM,LEAD-PEF	1.2nF,5%,1.6KV,TP,23*16*7.5,7.	SA
5	2201-000012	C512	C-CERAMIC,DISC	0.22NF,10%,1KV,Y5P,TP,6.3X5MM,5	SA
5	2401-000058	C513	C-AL	220uF,20%,100V,GP,TP,12.5x25,5	SA
5	2401-000031	C521	C-AL	47uF,20%,16V,GP,TP,5x11,5	SA
5	2202-002009	C530	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2401-000638	C531	C-AL	2.2uF,20%,350V,WT,TP,10x12.5mm	SA
5	2401-001576	C532	C-AL	47uF,20%,50V,GP,TP,8x11.5,5	SA
5	2401-002267	C533	C-AL	2.2uF,20%,250V,GP,TP,8x11.5,5	SA
5	2301-000213	C534	C-FILM,LEAD-PEF	220nF,5%,250V,TP,21.5x11,7.5	SA
5	2301-001480	C535	C-FILM,LEAD-PEF	2000NF,5%,100V,TP,17X16.5X9.5,7.5	SA
5	2401-001026	C536	C-AL	3.3UF,20%,50V,GP,TP,5X11,5	SA
5	2401-002300	C537	C-AL	47uF,20%,50V,GP,TP,6.3x11,5	SA
5	2305-000428	C541	C-FILM,LEAD-PEF	47nF,5%,250V,TP,11x9x4.5,5mm	SA
5	2401-000480	C551	C-AL	10uF,20%,50V,GP,TP,5x11,5	SA
5	2201-000129	C552	C-CERAMIC,DISC	0.1NF,10%,1KV,Y5P,TP,7X4MM,5	SA
5	2201-000285	C561	C-CERAMIC,DISC	1NF,10%,1KV,Y5P,TP,8X5MM,5	SA
5	2201-000285	C562	C-CERAMIC,DISC	1NF,10%,1KV,Y5P,TP,8X5MM,5	SA
5	2306-001011	C563	C-FILM,LEAD-PPF	56nF,5%,250V,TP,19x7.5x14.5,7.	SA
5	2301-000020	C564	C-FILM,LEAD-PEF	27nF,5%,100V,TP,7.3x4x12.5mm,5	SA
5	2301-000148	C565	C-FILM,LEAD-PEF	10nF,5%,100V,TP,7x3.2x7mm,5mm	SA
5	2201-000023	C603	C-CERAMIC,DISC	2.2NF,20%,250V,Y5U,TP,11X7MM,5	SA
5	2201-000023	C604	C-CERAMIC,DISC	2.2NF,20%,250V,Y5U,TP,11X7MM,5	SA
5	2401-000970	C606	C-AL	22uF,20%,50V,WT,TP,5x11,5	SA
5	2202-002009	C607	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2201-000325	C608	C-CERAMIC,DISC	2.2NF,10%,500V,Y5P,TP,9.5X4MM,5	SA
5	2201-000129	C609	C-CERAMIC,DISC	0.1NF,10%,1KV,Y5P,TP,7X4MM,5	SA
5	2201-000017	C610	C-CERAMIC,DISC	1NF,10%,50V,Y5P,TP,5X3.5MM,5	SA
5	2401-000611	C611	C-AL	1uF,20%,50V,WT,TP,5x11,5	SA
5	2305-000149	C613	C-FILM,LEAD-PEF	100nF,5%,100V,TP,12x12.5x6.5,5	SA
5	2301-000284	C614	C-FILM,LEAD-PEF	47nF,5%,100V,TP,8.5x12.5mm,5mm	SA
5	2401-001585	C615	C-AL	47uF,20%,50V,WT,TP,8x11.5,5	SA
5	2202-002009	C616	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2201-000023	C617	C-CERAMIC,DISC	2.2NF,20%,250V,Y5U,TP,11X7MM,5	SA
5	2401-000015	C618	C-AL	33uF,20%,50V,WT,-,6.3x11mm,2.5	SA
5	2201-000291	C619	C-CERAMIC,DISC	1NF,10%,500V,Y5P,TP,7.5X3.5MM,5	SA
5	2305-000178	C621	C-FILM,LEAD-PEF	10nF,5%,100V,TP,-,5mm	SA
5	2401-000039	C622	C-AL	1000uF,20%,16V,GP,TP,10x16,5	SA
5	2401-000025	C623	C-AL	100uF,20%,16V,GP,TP,6.3x11,5	SA
5	2401-000010	C624	C-AL	220uF,20%,16V,GP,-,6.3x11mm,2.	SA
5	2401-000010	C625	C-AL	220uF,20%,16V,GP,-,6.3x11mm,2.	SA
5	2401-000010	C626	C-AL	220uF,20%,16V,GP,-,6.3x11mm,2.	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	2401-000039	C627	C-AL	1000uF,20%,16V,GP,TP,10x16,5	SA
5	2401-000058	C628	C-AL	220uF,20%,100V,GP,TP,12.5x25,5	SA
5	2401-003826	C629	C-AL	220UF,20%,63V,LR,TP,10X25MM,5	SA
5	2201-000732	C630	C-CERAMIC,DISC	0.68NF,10%,1KV,Y5P,TP,7X4MM,5	SA
5	2401-000039	C631	C-AL	1000uF,20%,16V,GP,TP,10x16,5	SA
5	2401-000058	C633	C-AL	220uF,20%,100V,GP,TP,12.5x25,5	SA
5	2201-000017	C634	C-CERAMIC,DISC	1NF,10%,50V,Y5P,TP,5X3.5MM,5	SA
5	0203-001600	CIS10	TAPE-PAPER	#53128,0.15,5.5,2000M,BEIGE	SNA
5	0203-001599	CIS9	TAPE-KRAFT	#53110,0.1,6,2000M,BRN	SNA
5	BH71-40300A	CN420	PIN-HINGE	BRASS,D2.36!,HEAT/SINK,SN	SNA
5	BH71-40300A	CN421	PIN-HINGE	BRASS,D2.36!,HEAT/SINK,SN	SNA
5	3711-000217	CN602	CONNECTOR-HEADER	1WALL,2P,1R,7.92MM,STRAIGHT,SN,NTR	SA
5	0401-000005	D201	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D251	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D252	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0402-000274	D301	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0401-000005	D401	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D402	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0402-001118	D411	DIODE-RECTIFIER	UF1G,400V,1.2A,DO-204AC,TP	SA
5	0402-000274	D412	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0401-000004	D441	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0402-000274	D451	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0401-000005	D501	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D502	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D504	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D506	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D508	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D509	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0402-000274	D510	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0402-000012	D531	DIODE-RECTIFIER	UF4007,1KV,1A,DO-41,TP	SA
5	0402-000274	D532	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0402-000017	D533	DIODE-RECTIFIER	RGP02-12,1.2KV,0.5A,DO-204AL,TP	SA
5	0401-000005	D541	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0402-001114	D542	DIODE-RECTIFIER	1N4936GP,400V,1A,DO-201AD,TP	SA
5	0402-000546	D543	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41,TP	SA
5	0401-000005	D544	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D551	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0402-000012	D603	DIODE-RECTIFIER	UF4007,1KV,1A,DO-41,TP	SA
5	0402-000012	D604	DIODE-RECTIFIER	UF4007,1KV,1A,DO-41,TP	SA
5	0402-000546	D605	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41,TP	SA
5	0402-000546	D606	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41,TP	SA
5	0401-000005	D607	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D608	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D621	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0402-001194	D622	DIODE-RECTIFIER	UG2D,200V,2A,-,TP	SA
5	0402-000274	D623	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0402-000274	D624	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0402-001194	D627	DIODE-RECTIFIER	UG2D,200V,2A,-,TP	SA
5	0402-001118	D628	DIODE-RECTIFIER	UF1G,400V,1.2A,DO-204AC,TP	SA
5	6042-000001	EY301	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY302	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY401	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY402	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY403	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY404	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY405	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY411	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY415	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY422	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY423	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY454	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY455	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY501	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY502	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY503	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY504	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY505	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY506	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY507	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	6042-000001	EY601	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY602	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY603	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY604	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY605	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY606	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY607	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY608	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY621	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY622	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY623	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	BH71-40300A	GT401	PIN-HINGE	BRASS,D2.36!,HEAT/SINK,SN	SNA
5	BH71-40300A	GT402	PIN-HINGE	BRASS,D2.36!,HEAT/SINK,SN	SNA
5	BH71-40300A	GT601	PIN-HINGE	BRASS,D2.36!,HEAT/SINK,SN	SNA
5	BH71-40300A	GT602	PIN-HINGE	BRASS,D2.36!,HEAT/SINK,SN	SNA
5	1103-001150	IC241	IC-EEPROM	24C081,1Kx8,DIP,8P,9.2x6.4mm,2.7/5.5V,-25to+70C	SA
5	1203-000610	IC501	IC-PWM CONTROLLER	494,DIP,16P,300MIL,PLASTIC,40V,1W,0TO+70C,250MA,4.75/5.25V,ST	SA
5	BH39-40305U	JP_DHH	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP1	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP10	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP11	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP12	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP13	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP14	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP15	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP16	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP17	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP18	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP19	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP20	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP21	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP22	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP23	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP24	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP25	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP26	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP27	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP28	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP29	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP3	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP30	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP31	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP32	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP33	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP34	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP35	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP36	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP37	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP38	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP39	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP4	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP40	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP41	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP42	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP43	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP44	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP45	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP46	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP47	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP48	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP49	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP5	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP50	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP51	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP52	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP53	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP54	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP57	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP58	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	BH39-40305U	JP60	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP61	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP62	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP63	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP64	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP65	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP66	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP67	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP68	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP69	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP7	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP70	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP71	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP72	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP73	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP74	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP75	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP76	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP77	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP78	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP79	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP8	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP80	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP82	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP83	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP9	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	2701-000189	L218	INDUCTOR-AXIAL	0.47UH,10%,2534	SA
5	2701-000116	L501	INDUCTOR-AXIAL	10UH,10%,4298	SA
5	BH41-00270A	MP1.0	PCB MAIN	LE19IS,FR-1,1,1.0,1.6T,247*247,LE19,MAIN	SNA
5	0501-000122	Q321	TR-SMALL SIGNAL	2N3904,NPN,625mW,TO-92,TP,100-300	SA
5	0501-000581	Q322	TR-SMALL SIGNAL	2N3906,PNP,625mW,TO-92,TP,100-300	SA
5	0501-000586	Q323	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000586	Q403	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000303	Q404	TR-SMALL SIGNAL	KSA733,PNP,250mW,TO-92,TP,120-240	SA
5	0501-000586	Q411	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000303	Q412	TR-SMALL SIGNAL	KSA733,PNP,250mW,TO-92,TP,120-240	SA
5	0501-000586	Q455	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000586	Q456	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000586	Q457	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000586	Q458	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000404	Q459	TR-SMALL SIGNAL	KSD1616-Y,NPN,750mW,TO-92,TP,135-270	SA
5	0501-000122	Q502	TR-SMALL SIGNAL	2N3904,NPN,625mW,TO-92,TP,100-300	SA
5	0501-000581	Q503	TR-SMALL SIGNAL	2N3906,PNP,625mW,TO-92,TP,100-300	SA
5	0501-000122	Q523	TR-SMALL SIGNAL	2N3904,NPN,625mW,TO-92,TP,100-300	SA
5	0501-000586	Q541	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000143	Q542	TR-SMALL SIGNAL	2N6520,PNP,625mW,TO-92,TP,30-200	SA
5	0501-000413	Q551	TR-SMALL SIGNAL	KSP44,NPN,625mW,TO-92,TP,50-200	SA
5	0501-000122	Q601	TR-SMALL SIGNAL	2N3904,NPN,625mW,TO-92,TP,100-300	SA
5	0501-000404	Q604	TR-SMALL SIGNAL	KSD1616-Y,NPN,750mW,TO-92,TP,135-270	SA
5	0501-000010	Q621	TR-SMALL SIGNAL	KSC1008,NPN,800mW,TO-92,TP,120-240	SA
5	0501-000586	Q622	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000586	Q624	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000321	Q625	TR-SMALL SIGNAL	KSB1116-Y,PNP,750mW,TO-92,TP,135-270	SA
5	2001-000429	R201	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R202	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R203	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R204	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R205	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R206	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000800	R207	R-CARBON	5.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000739	R208	R-CARBON	4.7MOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R209	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R210	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R211	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R212	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R213	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R214	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R215	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000006	R216	R-CARBON	2.4KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	2001-000006	R217	R-CARBON	2.4KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000793	R218	R-CARBON	47OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R219	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R220	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R221	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R222	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R223	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R224	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R227	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000435	R228	R-CARBON	1MOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000435	R229	R-CARBON	1MOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R230	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000554	R231	R-CARBON	270OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000869	R232	R-CARBON	56OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000869	R233	R-CARBON	56OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R234	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R235	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R236	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R241	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R242	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R243	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R244	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000977	R301	R-CARBON	8.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2004-000216	R302	R-METAL	10Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2004-000616	R304	R-METAL	24Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2001-001078	R305	R-CARBON(S)	15KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2004-001005	R306	R-METAL	5.1Kohm,1%,1/4W,AA,TP,2.4x6.4m	SA
5	2004-004038	R307	R-METAL	4.3Kohm,1%,1/4W,AA,TP,2.4x6.4m	SA
5	2004-004231	R308	R-METAL(S)	2.4OHM,1%,1/2W,AA,TP,3.3X9MM	Y
5	2004-001391	R309	R-METAL(S)	2.2ohm,1%,1/2W,AA,TP,2.4x6.4mm	SA
5	2001-000037	R310	R-CARBON(S)	330OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000290	R311	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001053	R312	R-CARBON(S)	1.5OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000977	R313	R-CARBON	8.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R321	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000331	R322	R-CARBON	12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000302	R323	R-CARBON	10OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000864	R324	R-CARBON	56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000042	R325	R-CARBON	1KOHM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000281	R326	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001079	R327	R-CARBON(S)	15OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-001079	R328	R-CARBON(S)	15OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000319	R401	R-CARBON	120KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000221	R402	R-CARBON	1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000221	R403	R-CARBON	1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000490	R404	R-CARBON	200OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000739	R405	R-CARBON	4.7MOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000052	R406	R-CARBON(S)	3.3KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-001078	R407	R-CARBON(S)	15KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2003-000608	R408	R-METAL OXIDE(S)	270ohm,5%,3W,AA,TP,6x16mm	SA
5	2003-000763	R410	R-METAL OXIDE(S)	6.8ohm,5%,3W,AA,TP,6x16mm	SA
5	2003-000468	R411	R-METAL OXIDE(S)	10ohm,5%,1W,AA,TP,3.3x9mm	SA
5	2001-000008	R412	R-CARBON	15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2003-000005	R413	R-METAL OXIDE(S)	1ohm,5%,2W,AA,TP,4x12mm	SA
5	2001-000107	R415	R-CARBON(S)	150KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2004-001118	R431	R-METAL	5Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2001-000449	R432	R-CARBON	2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2004-004367	R433	R-METAL	90Kohm,1%,1/4W,AA,TP,6.2x2.6mm	SA
5	2001-000449	R434	R-CARBON	2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000010	R435	R-CARBON	68KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000356	R436	R-CARBON	150KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2004-001230	R437	R-METAL	75Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2004-000657	R438	R-METAL	27Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2004-000412	R439	R-METAL	18Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2001-000890	R440	R-CARBON	6.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000577	R441	R-CARBON	2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000563	R442	R-CARBON	27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R451	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R452	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	2001-000290	R453	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R454	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000411	R455	R-CARBON	18KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000411	R456	R-CARBON	18KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000411	R457	R-CARBON	18KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000411	R458	R-CARBON	18KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R459	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R460	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R461	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R462	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2003-000450	R463	R-METAL OXIDE(S)	100Kohm,5%,3W,AA,TP,6x16mm	SA
5	2003-000541	R464	R-METAL OXIDE(S)	1Kohm,5%,3W,AA,TP,6x16mm	SA
5	2003-000671	R465	R-METAL OXIDE(S)	390ohm,5%,2W,AA,TP,4x12mm	SA
5	2001-000290	R467	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2003-000514	R468	R-METAL OXIDE(S)	15ohm,5%,2W,AA,TP,4x12mm	SA
5	BH39-40305U	R469	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	2001-000241	R501	R-CARBON	1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R502	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000812	R503	R-CARBON	5.6KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000689	R504	R-CARBON	390KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000786	R505	R-CARBON	47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R506	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000331	R507	R-CARBON	12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R509	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000241	R510	R-CARBON	1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001153	R511	R-CARBON(S)	47OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-001144	R512	R-CARBON(S)	4.7KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2005-001172	R513	R-WIRE WOUND,NON	0.6ohm,5%,3W,AA,TP,5.5x15mm	SA
5	2003-000432	R515	R-METAL OXIDE(S)	1.5Kohm,5%,3W,AA,TP,6x16mm	SA
5	2004-001005	R516	R-METAL	5.1Kohm,1%,1/4W,AA,TP,2.4x6.4m	⚠ SA
5	2001-000878	R520	R-CARBON	6.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000800	R521	R-CARBON	5.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2004-001136	R522	R-METAL	6.8Kohm,1%,1/4W,AA,TP,2.4x6.4m	SA
5	2001-000734	R523	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2004-001298	R526	R-METAL	82Kohm,2%,1/4W,AA,TP,2.4x6.4mm	⚠ SA
5	2001-000429	R530	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000073	R531	R-CARBON	33KOHM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2004-000781	R532	R-METAL	330Kohm,1%,1/4W,AA,TP,2.4x6.4m	⚠ SA
5	2004-000560	R533	R-METAL	220Kohm,1%,1/4W,AA,TP,2.4x6.4m	⚠ SA
5	2001-000800	R534	R-CARBON	5.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2004-000252	R535	R-METAL	11Kohm,1%,1/4W,AA,TP,2.4x6.4mm	⚠ SA
5	2001-000591	R541	R-CARBON	3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R542	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2002-001091	R543	R-COMPOSITION	270KOHM,5%,1/2W,AA,TP,3X9MM	SA
5	2002-001062	R544	R-COMPOSITION	150Kohm,2%,1/2W,AA,TP,3.9x9mm	SA
5	2002-000121	R545	R-COMPOSITION	1Mohm,10%,1/2W,AA,TP,3.5x9.5mm	SA
5	2001-000734	R550	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R551	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000331	R553	R-CARBON	12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R554	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R555	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2002-001079	R556	R-COMPOSITION	470Kohm,5%,1/2W,AA,TP,4x10mm	SA
5	2002-001079	R557	R-COMPOSITION	470Kohm,5%,1/2W,AA,TP,4x10mm	SA
5	2001-000114	R558	R-CARBON(S)	180KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000114	R559	R-CARBON(S)	180KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2003-000514	R561	R-METAL OXIDE(S)	15ohm,5%,2W,AA,TP,4x12mm	SA
5	2001-000221	R562	R-CARBON	1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001129	R601	R-CARBON(S)	330KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-001129	R602	R-CARBON(S)	330KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2003-000738	R603	R-METAL OXIDE(S)	56Kohm,5%,2W,AA,TP,4x12mm	SA
5	2003-000014	R604	R-METAL OXIDE(S)	10Kohm,5%,3W,AA,TP,6x16mm	SA
5	2002-001103	R605	R-COMPOSITION	300Kohm,5%,1/2W,AA,TP,3.7x10.0mm	SA
5	2002-001103	R606	R-COMPOSITION	300Kohm,5%,1/2W,AA,TP,3.7x10.0mm	SA
5	2001-001116	R607	R-CARBON(S)	27OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000734	R608	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000780	R609	R-CARBON	470OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R610	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	BH39-40305U	R611	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	2001-000023	R621	R-CARBON	47OHM,5%,1/4W,AA,TP,2.4X6.4MM	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	2001-000027	R622	R-CARBON	100OHM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000613	R623	R-CARBON	3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000857	R624	R-CARBON	560OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R626	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R627	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000472	R628	R-CARBON	2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000786	R629	R-CARBON	47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2003-000473	R631	R-METAL OXIDE(S)	10ohm,5%,3W,AA,TP,6x16mm	SA
5	2001-001108	R632	R-CARBON(S)	22KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000613	R634	R-CARBON	3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	4715-001055	SK531	SURGE ABSORBER	1kV,+50-10%,-,-,RADIAL	SNA
5	6042-000002	TP501	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	2801-000006	X201	CRYSTAL-UNIT	12MHz,50ppm,28-AAM,S,35ohm,BK	SA
5	0403-000337	ZD201	DIODE-ZENER	UZ24BH,24.26-25.52V,500MW,DO-35,TP	SA
5	0403-001068	ZD202	DIODE-ZENER	UZ4.7BSA,4.44-4.68V,500MW,DO-34,TP	SA
5	0403-000361	ZD221	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD222	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD223	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD224	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD225	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD501	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-001167	ZD541	DIODE-ZENER	MTZJ30D,29.02-30.51V,500MW,DO-34,TP	SA
5	0403-001221	ZD542	DIODE-ZENER	UZ39BSB,35.36-37.19V,500MW,DO-34,TP	SA
5	0403-001068	ZD543	DIODE-ZENER	UZ4.7BSA,4.44-4.68V,500MW,DO-34,TP	SA
5	0403-001221	ZD601	DIODE-ZENER	UZ39BSB,35.36-37.19V,500MW,DO-34,TP	SA
5	0403-000361	ZD602	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
4	BH99-00030F	HS422	ASSY HEAT/SINK	HS TR,SCREW+NUT,IRFS630B(4),OIL SILICON	SNA
5	0205-001154	CIS	OIL-SILICON	G746,-,-	SNA
5	0505-001716	CIS	FET-SILICON	IRFS630B,N,200V,9A,0.4OHM,38W,TO-220F	SA
5	6006-001008	CIS	SCREW-ASS'Y MACH	WSP,BH,+,M3,L10,ZPC(YEL),SWRCH	SNA
5	6021-000118	CIS	NUT-HEXAGON	1C,M3,ZPC(YEL),SM20C	SNA
5	BH62-00044A	CIS	HEAT SINK-TR	AQ19FS,A1050S,T2.0,20,55,-,-,-	SNA
4	BH99-10019H	HS411	ASSY HEAT/SINK	H/S TR,SCREW+NUT,IRF634A,-,-,OIL SILICON,-,-	SNA
5	0205-001154	CIS	OIL-SILICON	G746,-,-	SNA
5	0505-001181	CIS	FET-SILICON	IRF634A,N,250V,8.1A,450mohm,74	SA
5	6006-001008	CIS	SCREW-ASS'Y MACH	WSP,BH,+,M3,L10,ZPC(YEL),SWRCH	SNA
5	6021-000118	CIS	NUT-HEXAGON	1C,M3,ZPC(YEL),SM20C	SNA
5	BH62-30024B	CIS	HEAT SINK-IC	SPC-1,T1,SN COATING,-	SNA
4	BN61-01137A	CIS16	SUPPORT-CLIP	IBM E74,NYLON 66,1.0,NTR	SNA
4	BP96-00065B	HS301	ASSY HEAT SINK P	BH62-00003B,SCREW,STV9325,OIL SILICON	N
5	0205-001154	H/S	OIL-SILICON	G746,-,-	SNA
5	1204-002262	H/S	IC-VERTICAL DEF.	STV9325,HEPTAWATT,7P,15.45x10.22mm,PLASTIC,35V,-,-40to+150C,ST,IC-VERTICAL DEF.	SNA
5	6003-000334	H/S	SCREW-TAPTITE	RH,+,2S,M3,L6,ZPC(YEL),SWRCH18	SNA
5	BH62-00003B	H/S	HEAT SINK-VERT	A1050S,T1.0,T1.0,-,DA,DB	SNA
4	BP96-00075D	HS601	ASSY HEAT SINK P	BH62-00052A,SPRING,8SA0965,SILICON RUBBER	SNA
5	BH13-00049A	H/S	IC HYBRID	FS8S0965RCB(DP906C),LE19IS,5,-25 to 85,TO-220(FORMING),35,ST	SA
5	BH61-00004A	H/S	SPRING ETC-TR	CDA,CDB,SUS304,-,-,-,-,-,T0.5,-,-,-	SNA
5	BH62-00052A	H/S	HEAT SINK-POWER	M782,A1050S,T1.0,W25,L55,-,BH62,-	SNA
5	BH62-20001B	H/S	TUBE-RUBBER	CSQ4357,W25*L20*T0.45,-,-,-,-	SNA

7-2-2 LE19IS Video PCB Parts

Level	Loc. No.	Code No.	Description	Specification	Remarks
3	BH94-00978A	-	ASSY PCB VIDEO-ST	LE19IS	SNA
4	6003-001023	-	SCREW-TAPTITE	RWH,+,B,M3,L10,ZPC(YEL),SWRCH1	SNA
4	BH39-00386A	CIS	CBF-GROUND ASS'Y	MS17J0,8*0.16*16TA,1P/2P,80MM,35750-1010,EARTH PLATE CLIP,BK,8*0.16*16TA	SA
4	BH63-00131A	CIS1	SHIELD-VIDEO	LE17KS,SPTE,T0.2	SNA

Level	Loc. No.	Code No.	Description	Specification	Remarks
4	0204-002426	CIS3	FLUX	DF-201TVS,MIX,0.820,FLUX13%,14KG,-	SNA
4	0204-002420	CIS4	SOLVENT	1M-1000,C3H70H,96,-,-	SNA
4	BH68-00001A	CIS40	LABEL-MARK CDT	ART-PAPER100G,-,WHT,BLK,-,ALL,CDT	SNA
4	3711-004236	CN101	CONNECTOR-HEADER	BOX,6P,1R,2MM,STRAIGHT,SN	SNA
4	BH39-00015A	CN102	CBF-HARNESS	13P/14P,200MM,WHT/BLK/RED/BLU,UL1007,AWG26,SMH200-13/YBNH200-14	SA
4	BH13-00050A	IC102	IC HYBRID	NT6813K-30031,NT6813K-30031,24P,-55 to +150,240mA,-0.5 to 6V,ST	SA
4	3704-001203	SK101	SOCKET-CRT	9P,29PI,22.5PI,NI+SN,-	SNA
4	BH96-00283B	HS106	ASSY HEAT SINK P	BH62-00054A,SCREW,LM2463,OIL SILICON	SNA
5	0205-001154	H/S	OIL-SILICON	G746,-,-	SNA
5	1201-002116	H/S	IC-VIDEO AMP	LM2463,TO-220,11P,17.5x20.01mm,-,-20,PLASTIC,100V,-,0to70C,-,-,-,-,-,ST	SA
5	6003-000334	H/S	SCREW-TAPTITE	RH,+,2S,M3,L6,ZPC(YEL),SWRCH18	SNA
5	BH62-00054A	H/S	HEAT SINK-PS	LEO,A1050S,2.0,112,25	SNA
4	BH97-00510A	-	ASSY AUTO-(VIDEO)ST	LE19IS	SNA
5	3301-001450	BD101	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD102	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD104	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001660	BD105	BEAD-RADIAL	100OHM,3.5X9.0X0.8,50MA,TP,K-150,0OHM	SA
5	3301-001450	BD106	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	2202-002009	C101	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2401-000025	C103	C-AL	100uF,20%,16V,GP,TP,6.3x11,5	SA
5	2401-000603	C104	C-AL	1UF,20%,50V,GP,TP,5X11,2	SA
5	2201-000019	C106	C-CERAMIC,DISC	10nF,+80-20%,500V,Y5V,TP,13.5x4mm,5	SA
5	2401-003036	C111	C-AL	100uF,20%,16V,GP,TP,5X11mm,5mm	SA
5	2202-002009	C112	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2401-003036	C113	C-AL	100uF,20%,16V,GP,TP,5X11mm,5mm	SA
5	2201-000119	C114	C-CERAMIC,DISC	100NF,+80-20%,50V,Y5V,TP,8X3MM,5	SA
5	2401-003036	C115	C-AL	100uF,20%,16V,GP,TP,5X11mm,5mm	SA
5	2202-002009	C116	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2301-000148	C117	C-FILM,LEAD-PEF	10nF,5%,100V,TP,7x3.2x7mm,5mm	SA
5	2201-000483	C118	C-CERAMIC,DISC	0.033NF,5%,50V,C0G,TP,5X3.5MM,5	SA
5	2401-003036	C119	C-AL	100uF,20%,16V,GP,TP,5X11mm,5mm	SA
5	2202-002009	C120	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2401-003036	C121	C-AL	100uF,20%,16V,GP,TP,5X11mm,5mm	SA
5	2202-002009	C122	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2301-000010	C123	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2401-000049	C124	C-AL	47uF,20%,100V,WT,TP,10x16,5	SA
5	2202-002009	C125	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2201-000119	C126	C-CERAMIC,DISC	100NF,+80-20%,50V,Y5V,TP,8X3MM,5	SA
5	2201-000119	C131	C-CERAMIC,DISC	100NF,+80-20%,50V,Y5V,TP,8X3MM,5	SA
5	2201-000019	C132	C-CERAMIC,DISC	10nF,+80-20%,500V,Y5V,TP,13.5x4mm,5	SA
5	2201-000154	C133	C-CERAMIC,DISC	10NF,+80-20%,2KV,Y5P,TP,20X5MM,7.5	SA
5	2202-000286	C134	C-CERAMIC,MLC-AXIAL	56pF,5%,50V,SL,TP,1.9x3.5,-	SA
5	2202-000286	C135	C-CERAMIC,MLC-AXIAL	56pF,5%,50V,SL,TP,1.9x3.5,-	SA
5	2202-002009	CB01	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2202-002009	CB02	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2301-000010	CB03	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2401-003911	CB04	C-AL	1uF,20%,160V,BP,TP,6.3x11mm,5	SA
5	2202-002009	CG01	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2202-002009	CG02	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2301-000010	CG03	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2401-003911	CG04	C-AL	1uF,20%,160V,BP,TP,6.3x11mm,5	SA
5	6502-000001	CIS	CABLE CLAMP	DAWH-5NB,D15,L35,NYLON66,NTR	SNA
5	0203-001599	CIS6	TAPE-KRAFT	#53110,0.1,6,2000M,BRN	SNA
5	0203-001600	CIS7	TAPE-PAPER	#53128,0.15,5.5,2000M,BEIGE	SNA
5	BH71-40300A	CN_G2	PIN-HINGE	BRASS,D2.36!,HEAT/SINK,SN	SNA
5	BH71-40300A	CN_GND	PIN-HINGE	BRASS,D2.36!,HEAT/SINK,SN	SNA
5	2202-002009	CR01	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2202-002009	CR02	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2301-000010	CR03	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2401-003911	CR04	C-AL	1uF,20%,160V,BP,TP,6.3x11mm,5	SA
5	0401-000005	DB01	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	DB02	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000004	DB03	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DB04	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DB05	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000005	DG01	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	DG02	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	0401-000004	DG03	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DG04	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DG05	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000005	DR01	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	DR02	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000004	DR03	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DR04	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DR05	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	6042-000001	EY1	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY2	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY3	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY4	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY5	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	BH13-00022A	IC104	IC HYBRID-BIAS CLAMP	LM2480NA,PN15H/17L,8P,0to+70C,DIP,3mA,85V,ST	SA
5	BH39-40305U	JP101	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP102	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP103	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP104	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP105	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	2701-001062	LB01	INDUCTOR-AXIAL	0.12UH,10%,3070	SA
5	2701-001092	LB02	INDUCTOR-AXIAL	0.07uH,10%,2360	SA
5	2701-001062	LG01	INDUCTOR-AXIAL	0.12UH,10%,3070	SA
5	2701-001092	LG02	INDUCTOR-AXIAL	0.07uH,10%,2360	SA
5	2701-001062	LR01	INDUCTOR-AXIAL	0.12UH,10%,3070	SA
5	2701-001092	LR02	INDUCTOR-AXIAL	0.07uH,10%,2360	SA
5	BH41-00271A	MP1.0	PCB-VIDEO	LE19IS,FR-1,1,1.0,1.6T,82.3*123.5,LE19,6,VIDEO	SNA
5	2001-000577	R102	R-CARBON	2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R103	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R105	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R106	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000016	R107	R-CARBON(S)	1OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000435	R111	R-CARBON	1MOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000812	R112	R-CARBON	5.6KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R113	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R114	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001138	R131	R-CARBON(S)	390OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000037	R132	R-CARBON(S)	330OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000947	R134	R-CARBON	7.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000084	R135	R-CARBON	100Kohm,5%,1/4W,AA,TP,2.4x6.4mm	SA
5	2001-000969	RB01	R-CARBON	75OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000969	RB02	R-CARBON	75OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	RB03	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001187	RB05	R-CARBON(S)	75OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000429	RB06	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001129	RB07	R-CARBON(S)	330KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000022	RB08	R-CARBON(S)	33OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000969	RG01	R-CARBON	75OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000969	RG02	R-CARBON	75OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	RG03	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001199	RG05	R-CARBON(S)	91OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000429	RG06	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001129	RG07	R-CARBON(S)	330KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000022	RG08	R-CARBON(S)	33OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000969	RR01	R-CARBON	75OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000969	RR02	R-CARBON	75OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	RR03	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001187	RR05	R-CARBON(S)	75OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000429	RR06	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001129	RR07	R-CARBON(S)	330KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000022	RR08	R-CARBON(S)	33OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	1405-001064	SK104	SURGE ABSORBER	400V,20%,-,-,AXIAL	SA
5	4715-001065	SK105	SURGE ABSORBER	200V,20%,-,-,RADIAL	SNA
5	4715-001055	SK108	SURGE ABSORBER	1kV,+50-10%,-,-,RADIAL	SNA
5	4715-001065	SKB01	SURGE ABSORBER	200V,20%,-,-,RADIAL	SNA
5	4715-000102	SKG01	SURGE ABSORBER	200V,20%,1000A,-,RADIAL	SNA
5	4715-000102	SKR01	SURGE ABSORBER	200V,20%,1000A,-,RADIAL	SNA
5	0403-001068	ZD105	DIODE-ZENER	UZ4.7BSA,4.44-4.68V,500MW,DO-34,TP	SA

7-2-3 LE19IS Others

Level	Loc. No.	Code No.	Description	Specification	Remarks
2	BH90-00605A	-	ASSY COVER FRONT	LE19IS,EDC	SNA
3	6003-000009	C/F+C/R	SCREW-TAPTITE	BH,+,B,M4,L16,ZPC(YEL),SWRCH18	SNA
3	6006-001119	C/F+CDT	SCREW-ASS'Y TAPT	WC,BH,+,M5,L25,ZPC(YEL),SWRCH18A	SNA
3	BH96-00278A	C/F	ASSY COVER P-FRONT	LE19IS,ABS HB IV16	SNA
2	BH90-00617A	-	ASSY COVER REAR	LE19IS,EDC	SNA
3	BH63-00137A	C/R	COVER-REAR	LE19IS,ABS HB,IV16	SNA
2	BH90-00628A	-	ASSY STAND	LE19IS,EDC	SNA
3	BH96-00273A	STD	ASSY STAND P	LE19IS,ABS HB IV16	SNA
2	BH91-00843N	-	ASSY CDT-ST	LE19IS	SNA
3	0203-000005	CDT	TAPE-ACETATE	SGT730,T0.26,W19,L3000,BLK	SNA
3	0204-002421	CDT	COMPOUND	KS650N,-,0.9-1.1,1L,20L,-	SNA
3	3302-000006	CDT	MAGNET-RUBBER	AF,14G,1620-1980G,0.58-0.9MGOe	SA
3	3309-000002	CDT	MAGNET-SHEET	5x20x80mm,UL94V-0,2	SA
3	BH03-00047U	CDT	CDT-ST	M46QCK761X216(T4),84,19,0.25,29.1,IFT,H/C,NH,TCO,TILT,4	SA
3	BH68-30003C	CDT	LABEL-00,HIGH,VOLTAGE	SS,ART100G,30*33,YEL	SNA
3	BH96-00294A	CDT	ASSY D-COIL P	19 inch,BH27-00147A,BH96-00288A	SNA
2	BH91-00884A	-	ASSY SHIELD	LE19IS	SNA
3	0201-001059	CIS	ADHESIVE-SIL	#9590,WHT,-,CARTRIGE	SNA
3	6003-000010	SH/COV+SH/BTM	SCREW-TAPTITE	BWH,+,B,M3,L10,ZPC(YEL),SWRCH1	SA
3	BH96-00280A	CIS	ASSY MISC P-SHIELD COVER	LE19IS,SECC T0.5,AL T0.25	SNA
2	BH91-00969P	-	ASSY CHASSIS-SC	LEO	SNA
2	BH92-01068A	-	ASSY P/MATERIAL	LE19IS	SNA
3	0203-001102	P/M	TAPE-OPP MASKING	OPP-2,T0.05,W100,L400M,CLR	SNA
3	6902-000001	P/M	BAG AIR	LDPE,T0.2,L1800,W1000,TRP,,,LDPE ONLY	SNA
3	6902-000108	P/M	BAG PE	HDPE,T0.015,L1100,W1120,TRP,28,4,PE MARK	SNA
3	6902-000379	P/M	BAG AIR	HDPE,T0.2,L1800,W1000,TRP,,,PAPER	SNA
3	6902-000609	P/M	BAG ROLL	LDPE,T0.05,W2400,L1000,TRP,-,-	SNA
3	BH69-00565A	P/M	CUSHION	LE19IS,EPS M50,DF	SNA
3	BH69-40380A	P/M	PACKING-PAD	DW-2,500X2200X200,-,CGK5527	SNA
2	BH92-01160B	-	ASSY LABEL	LEO	SNA
3	BH68-00565A	LABEL	LABEL RATING-00	ALL,SS,PE,T0.05,90*65,BLK,POLYESTER,NO SILK	SNA
2	BH92-01162W	-	ASSY ACCESSORY	LEO	SNA
3	BH96-00297W	UNIT/ACCESSORY	ASSY ACCESSORY	LEO	SNA
4	0203-000214	ACCESSORY	TAPE-OPP MASKING	OPP/W50/CLR,T0.05,W50,L400000,	SNA
4	6902-000110	ACCESSORY	BAG PE	LDPE,T0.05,L356,W240,TRP,28,2,PE MARK	SNA
4	AA68-40065B	ACCESSORY	CARD-01,REGISTRATION	,SEA,A5,ENG,A/P220,2P(SIDES),4	SNA
4	BH39-10339X	ACCESSORY	CBF POWER CORD	DET,SVT,125V/7A,BLK,1830,WALL(ST),MSP-33,MSC-30	SA
4	BH68-00261F	ACCESSORY	CARD WARRANTY-03	SyncMaster14-1,ADC,MOJO180G,E/F,USA	SNA
4	BH68-00261R	ACCESSORY	MANUAL-00	3 MONTHS CRM CARD,SECA,E/F,CANADA,MOJO120G,173,234	SNA
4	BH68-00344C	ACCESSORY	CARD WARRANTY-00	SECA W'TY & CRM CARD,SECA,MOJO100G,E/F,CANADA	SNA
4	BH68-70033A	ACCESSORY	CARD-WARRANTY(BLOC)-01	ALL,SEA/SECA,USA/CANADA	SNA
4	BH96-00296A	ACCESSORY	ASSY MANUAL P-IB+QSG	795DF,SyncMaster,W/W,27Lang,BH59-362A+BH68-376J	SNA
5	BH59-00362A	I/B	S/W DRIVER-00,IB	793S,795DF,W/W,SYNCMASTER,27LANG	SNA
5	BH68-00376J	QUICK	MANUAL-01	AN_QUICK SETUP GUIDE,SYNCMASTER,E/F/S/G/P/I..14LANGS,W/W,MOJO100G,298,420	SNA
2	BH92-01163A	-	ASSY BOX	LEO	SNA
3	BH68-00530B	BOX	LABEL BOX-01	LABEL-BARCODE,CE+3Y W/T+TCO03,MOJO 90G,WHT	SNA
3	BH69-00572A	BOX	BOX-MONITOR(CDT)	S/M997DF(LE19IS),W/W,DW3,YEL,A-1,W542*D592*H477	SNA

7-3-1 LE19IT Main PCB Parts

Level	Loc. No.	Code No.	Description	Specification	Remarks
0	LE19ITBB/EDC				
1	ST-LE19ITBB/EDC	-	1	SDI,HIGH-CON(DF-T)	-
3	BH94-00976A	-	ASSY PCB MAIN-ST	LE19IS,EDC	SNA
4	2306-000147	C414	C-FILM,LEAD-PPF	1uF,5%,250V,BK,26x24x15,22.5mm	SA
4	2306-000263	C452	C-FILM,LEAD-PPF	770nF,5%,250V,BK,26x21.5x13.5,	SA
4	2301-001195	C601	C-FILM,LEAD-PPF	150nF,10%,275VAC,BK,26x16.5x7,	SA
4	2301-001195	C602	C-FILM,LEAD-PPF	150nF,10%,275VAC,BK,26x16.5x7,	SA
4	2401-003619	C605	C-AL	270uF,20%,450V,GP,BK,25.4x50mm,10	SA
4	BH63-00134A	CIS1	SHIELD-BOTTOM	LE17KS,SECC,T1.0	SNA
4	BH63-00124A	CIS2	SHIELD-IC	LE17KS,SPTE,T0.2	SNA
4	BH63-00143A	CIS3	COVER-PCB R	LE17KS,ABS PC,IV16	SNA
4	BH63-00144A	CIS4	COVER-PCB L	LE17KS,ABS PC,IV16	SNA
4	BH68-00001A	CIS40	LABEL-MARK CDT	ART-PAPER100G,-,WHT,BLK,-,ALL,CDT	SNA
4	0204-002426	CIS6	FLUX	DF-201TVS,MIX,0.820,FLUX13%,14KG,-	SNA
4	0204-002420	CIS7	SOLVENT	1M-1000,C3H70H,96,-,-	SNA
4	3711-003895	CN201	CONNECTOR-HEADER	BOX,13P,1R,2mm,STRAIGHT,SN	SA
4	3711-003843	CN202	CONNECTOR-HEADER	BOX,8P,1R,2mm,STRAIGHT,SN	SA
4	3711-004484	CN203	CONNECTOR-HEADER	BOX,5P,1R,2mm,STRAIGHT,SN	SA
4	3711-000885	CN321	CONNECTOR-HEADER	3WALL,3P,1R,2.5mm,STRAIGHT,SN	SA
4	3711-005055	CN401	CONNECTOR-HEADER	1WALL,4P,1R,10MM/8.0MM,STRAIGHT,SN-PB,WHT	SA
4	3721-001053	CN601	PLUG-AC POWER	3P,-,-,NI	SNA
4	3301-000130	CORE_1	CORE-FERRITE	AC,23.5x9.4x12.6mm,1500,2800G	SNA
4	3301-001264	CORE_2	CORE-FERRITE	AC,18.2X9.7X28.2MM,1500,2800GAUSS	SNA
4	0402-001441	D403	DIODE-RECTIFIER	-,40V,3A,DO-201AD,BK	SA
4	0402-001295	D505	DIODE-RECTIFIER	GUR460L-5700,600V,4A,DO-201AD,BK	SA
4	0402-001295	D507	DIODE-RECTIFIER	GUR460L-5700,600V,4A,DO-201AD,BK	SA
4	0402-001227	D601	DIODE-BRIDGE	D3SBA60,600V,2.3A,SIP-4,BK	SA
4	0402-000005	D626	DIODE-RECTIFIER	31DF4,400V,3A,DO-201AD,BK	SA
4	6003-000122	FBT+H/S	SCREW-TAPTITE	BH,+,B,M4,L12,ZPC(YEL),SWRCH18	SNA
4	3601-001303	FH1	FUSE-RADIAL LEAD	250V,4A,TIME-LAG,CERAMIC,5X20MM	SA
4	6502-000127	HS601_CLAMP1	CABLE CLAMP	DAWH-18NB,ID15,-,NYLON66,NTR	SNA
4	6502-001058	HS601_CLMAP2	CABLE CLAMP	DAWH-50N,ID16.6,-,NYLON6/6,NTR	SNA
4	3704-001071	IC201_SOCKET	SOCKET-IC	42P,DIP,SN,1.778mm	SA
4	1204-002259	IC401	IC-DEF. PROCESSOR	STV9118,SDIP,32P,27.94x8.89mm,PLASTIC,13.2V,-,0to+70C,ST,IC-DEF. PROCESSOR	SNA
4	1203-003240	IC621	IC-POSI.FIXED REG.	L78M05,IPAK,3P,6.5x6.1mm,PLASTIC,4.75/5.25V,-,0to+150C,0.5A,-,ST	SA
4	1203-000165	IC622	IC-POSI.ADJUST REG.	78R12,TO-220,4P,-,PLASTIC,11.7/12.3V,1.5W,-20TO+80C,1A,-,ST	SA
4	BH27-00134A	L411	COIL CHOKE	100UH,CDTM0,100UH,10%,0.20HM,5.0A,AR8X25,60.5TS,18X40MM,11MM,USTC0.12X20,TR,-10C	SA
4	BH27-00150A	L441	COIL LINEARITY	HL-1527C,5.2uH,YL8115X27.5,11mm,18x17x55mm,15©™%6.5t°æ0.5t,22T/1000T,BK,20%,0.0	⚠ SNA
4	BH27-00061A	L601	COIL FILTER	-,33.0mH,0.1ohm,72Ts,28.*28,-,BK,SQE-2828,3A,-,-	SA
4	6003-001023	M/PCB+SH/BTM	SCREW-TAPTITE	RWH,+,B,M3,L10,ZPC(YEL),SWRCH1	SNA
4	0505-001689	Q401	FET-SILICON	IRFU210B,N,200V,2.7A,1.5OHM,2.5W,I-PAK	SA
4	0505-001689	Q561	FET-SILICON	IRFU210B,N,200V,2.7A,1.5OHM,2.5W,I-PAK	SA
4	2005-001163	R409	R-WIRE WOUND,NON	0.68ohm,1%,3W,AA,TP,5.5x15mm	SA
4	2003-000695	R414	R-METAL OXIDE(S)	430ohm,5%,3W,AA,TP,6x16mm	SA
4	3501-001111	RL601	RELAY-POWER	12VDC,250MW,5000MA,1FORMA,15MS,5MS	SA
4	6003-000133	SH/BTM+AC/SOCK	SCREW-TAPTITE	BH,+,S,M4,L8,ZPC(YEL),SWRCH18A,-	SNA
4	BH39-00453A	SIGNAL_CABLE	CBF SIGNAL	LE19IS,15P/06P,08P,20276-N1,1830mm,UL20276,BLACK,D-SUB/MALE,AWG28/30,30V,ATT. TY	SNA
4	BH26-00090B	T401	TRANS HORIZ.DRIVE	EI-1916,AN19J,7P,35.0MH,185TS/13TS/95TS,73.0UH,7.5/0.05OHM,PL3,EI-1916,170UH MAX	⚠ SA
4	BH26-00174A	T411	TRANS-H PULSE	ER-2828,LE19IS,10P,500uH,0.70uH,0.2/0.030,PL-,DMR30,ER-2828,230uH,BK	SNA
4	BH26-00084A	T501	TRANS FBT	FQM19A005,PS17N0,122UH,SM19C,FUR3757SU,113.2MOHM,80,14P,-10~+60,BK,27KV	⚠ SA
4	BH26-00086A	T561	TRANS-FOCUS	EE1916,5P,2.0MH MIN,290MH MIN,0.85OHM/32.0OHM,EE1916(PL3,SL-2),EE19*16,23.0UH MA	⚠ SA
4	BH26-00172A	T601	TRANS SWITCHING	LE19IS,90~264V,FERRITE,ER-3942	SNA
4	BH26-00163A	T602	TRANS	UU-1116,CU17K,5,18mH min,18mH min,2.7ohm MAX,10 ~ 55,FERRITE,UU-1116 SB-5S	SA
4	1404-001264	TH601	THERMISTOR-PTC	4.5OHM,+30/-20%,220V,290VAC,21A,-,TR	SA
4	1404-001020	TH602	THERMISTOR-NTC	8ohm,15%,-,17mW/C,BK	SA
4	BH96-00285A	HS490	ASSY HEAT SINK P	BH62-00055A,SPRING,J6920,FFAF10U170S,2SK2761,OIL SILICON	SNA
5	0205-001154	H/S	OIL-SILICON	G746,-,-	SNA
5	0402-001520	H/S	DIODE-RECTIFIER	FFAF10U170S,1700V,10A,DO-201AD,ST	SA
5	0502-001259	H/S	TR-POWER	FJAF6920A,NPN,60000mW,TO-3PF,ST,6-9	SA
5	0505-001266	H/S	FET-SILICON	2SK2761-01MR,N,600V,10A,0.85oh	SA
5	BH61-70003A	H/S	SPRING ETC	CVT4857,STS304-W1/2H,W3.8,-,L30,L30,-,T0.5,DEGRE,W3.8,STS304-W1/2H	SNA
5	BH62-00055A	H/S	HEAT SINK-PS	NEO,A1050S,2.0,80,100	SNA
4	BH97-00505C	MICOM	ASSY MICOM	LE19IS	SA
5	0903-001194	IC201	IC-MICROCONTROLLER	3P863,8Bit,SDIP,42P,600MIL,12MHz,ST,CMOS,PLASTIC,5V,-,-40to+85C,1040BYTE,48KBYTE	SNA
5	BH82-00020J	CIS	A/S MICOM	LE19IS	SNA

Level	Loc. No.	Code No.	Description	Specification	Remarks
4	BH97-00508A	-	ASSY AUTO-(MAIN)ST	LE19IS	SNA
5	3301-000011	BD201	BEAD-AXIAL	,3.5x1.0x5.7mm,,BK,,,	SA
5	3301-000011	BD202	BEAD-AXIAL	,3.5x1.0x5.7mm,,BK,,,	SA
5	3301-000011	BD203	BEAD-AXIAL	,3.5x1.0x5.7mm,,BK,,,	SA
5	3301-000011	BD402	BEAD-AXIAL	,3.5x1.0x5.7mm,,BK,,,	SA
5	3301-000011	BD411	BEAD-AXIAL	,3.5x1.0x5.7mm,,BK,,,	SA
5	3301-000011	BD412	BEAD-AXIAL	,3.5x1.0x5.7mm,,BK,,,	SA
5	3301-000011	BD431	BEAD-AXIAL	,3.5x1.0x5.7mm,,BK,,,	SA
5	3301-000011	BD501	BEAD-AXIAL	,3.5x1.0x5.7mm,,BK,,,	SA
5	3301-001450	BD601	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	2201-000119	C201	C-CERAMIC,DISC	100NF,+80-20%,50V,Y5V,TP,8X3MM,5	SA
5	2401-000050	C202	C-AL	10uF,20%,16V,GP,TP,5x11,2.5	SA
5	2201-000389	C203	C-CERAMIC,DISC	0.022NF,5%,50V,C0G,TP,5X3MM,5	SA
5	2201-000389	C204	C-CERAMIC,DISC	0.022NF,5%,50V,C0G,TP,5X3MM,5	SA
5	2201-000144	C205	C-CERAMIC,DISC	0.1NF,5%,50V,C0G,TP,8.5X3MM,5	SA
5	2201-000017	C206	C-CERAMIC,DISC	1NF,10%,50V,Y5P,TP,5X3.5MM,5	SA
5	2201-000374	C207	C-CERAMIC,DISC	0.22NF,5%,50V,C0G,TP,10.5X3MM,5	SA
5	2401-000603	C208	C-AL	1UF,20%,50V,GP,TP,5X11,2	SA
5	2401-000603	C209	C-AL	1UF,20%,50V,GP,TP,5X11,2	SA
5	2401-000603	C210	C-AL	1UF,20%,50V,GP,TP,5X11,2	SA
5	2401-000603	C211	C-AL	1UF,20%,50V,GP,TP,5X11,2	SA
5	2201-000389	C212	C-CERAMIC,DISC	0.022NF,5%,50V,C0G,TP,5X3MM,5	SA
5	2401-002075	C260	C-AL	4.7uF,20%,50V,GP,TP,5x11,5	SA
5	2401-002463	C301	C-AL	470uF,20%,16V,GP,TP,8x11.5,5	SA
5	2301-000174	C302	C-FILM,LEAD-PEF	15nF,5%,100V,TP,7.2x4.0x7.5mm,	SA
5	2301-000148	C303	C-FILM,LEAD-PEF	10nF,5%,100V,TP,7x3.2x7mm,5mm	SA
5	2401-000852	C304	C-AL	220uF,20%,35V,GP,TP,8x11.5mm,5	SA
5	2305-000004	C305	C-FILM,LEAD-PEF	220nF,10%,100V,TP,12.7x16,5mm	SA
5	2301-000010	C306	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2401-002463	C307	C-AL	470uF,20%,16V,GP,TP,8x11.5,5	SA
5	2401-001914	C309	C-AL	1uF,20%,50V,BP,TP,5x11,5	SA
5	2301-000148	C310	C-FILM,LEAD-PEF	10nF,5%,100V,TP,7x3.2x7mm,5mm	SA
5	2301-000188	C312	C-FILM,LEAD-PEF	1nF,5%,100V,TP,10.5x12.5x6.5,5	SA
5	2201-000119	C321	C-CERAMIC,DISC	100NF,+80-20%,50V,Y5V,TP,8X3MM,5	SA
5	2401-000025	C322	C-AL	100uF,20%,16V,GP,TP,6.3x11,5	SA
5	2301-000168	C331	C-FILM,LEAD-PEF	150nF,5%,100V,TP,11.5x19mm,7.5	SA
5	2305-000237	C332	C-FILM,LEAD-PEF	1uF,5%,63V,TP,7.5x15.5mm,5mm	SA
5	2401-000031	C333	C-AL	47uF,20%,16V,GP,TP,5x11,5	SA
5	2401-000050	C401	C-AL	10uF,20%,16V,GP,TP,5x11,2.5	SA
5	2401-001218	C402	C-AL	4.7uF,20%,100V,WT,TP,5x11,5	SA
5	2301-000010	C403	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2301-000020	C404	C-FILM,LEAD-PEF	27nF,5%,100V,TP,7.3x4x12.5mm,5	SA
5	2301-001441	C405	C-FILM,LEAD-PPF	2nF,3%,1.6kV,TP,20x2.5x11mm,7.5	⚠ SA
5	2309-000106	C406	C-FILM,LEAD-OTHER	2.2nF,5%,1.6KV,TP,23x16x9,7.5m	⚠ SA
5	2401-003826	C411	C-AL	220UF,20%,63V,LR,TP,10X25MM,5	SA
5	2201-000285	C412	C-CERAMIC,DISC	1NF,10%,1KV,Y5P,TP,8X5MM,5	SA
5	2201-000012	C413	C-CERAMIC,DISC	0.22NF,10%,1KV,Y5P,TP,6.3X5MM,5	SA
5	2201-000003	C415	C-CERAMIC,DISC	0.068NF,10%,2KV,SL,TP,7X5MM,5	SA
5	2201-000732	C417	C-CERAMIC,DISC	0.68NF,10%,1KV,Y5P,TP,7X4MM,5	SA
5	2401-002463	C431	C-AL	470uF,20%,16V,GP,TP,8x11.5,5	SA
5	2305-000665	C432	C-FILM,LEAD-PEF	100nF,5%,63V,TP,7.5x4.0x5.0mm,	SA
5	2301-000148	C433	C-FILM,LEAD-PEF	10nF,5%,100V,TP,7x3.2x7mm,5mm	SA
5	2202-000573	C434	C-CERAMIC,MLC-RADIAL	0.82NF,5%,50V,C0G,TP,5.1X3.2X5.1MM,5	SA
5	2301-000020	C435	C-FILM,LEAD-PEF	27nF,5%,100V,TP,7.3x4x12.5mm,5	SA
5	2401-002075	C436	C-AL	4.7uF,20%,50V,GP,TP,5x11,5	SA
5	2401-000603	C437	C-AL	1UF,20%,50V,GP,TP,5X11,2	SA
5	2401-000031	C438	C-AL	47uF,20%,16V,GP,TP,5x11,5	SA
5	2301-000188	C439	C-FILM,LEAD-PEF	1nF,5%,100V,TP,10.5x12.5x6.5,5	SA
5	2301-000004	C440	C-FILM,LEAD-PEF	2.2nF,5%,100V,TP,5.5X10X2.9,5m	SA
5	2301-000106	C441	C-FILM,LEAD-PEF	1.5nF,0.05,100V,TP,10.5*12.5*6	SA
5	2301-000016	C442	C-FILM,LEAD-PEF	22nF,5%,100V,TP,7.2x4.5x9.0mm,	SA
5	2301-000168	C443	C-FILM,LEAD-PEF	150nF,5%,100V,TP,11.5x19mm,7.5	SA
5	2301-000188	C444	C-FILM,LEAD-PEF	1nF,5%,100V,TP,10.5x12.5x6.5,5	SA
5	2301-001249	C451	C-FILM,LEAD-PPF	68nF,5%,400V,TP,19x7x15mm,7.5	SA
5	2306-000006	C453	C-FILM,LEAD-PPF	330nF,5%,250V,TP,20x18.5x10.5,	SA
5	2306-000131	C454	C-FILM,LEAD-PPF	150nF,5%,250V,TP,19x16x7.5,7.5	SA
5	2301-001249	C455	C-FILM,LEAD-PPF	68nF,5%,400V,TP,19x7x15mm,7.5	SA
5	2301-001067	C456	C-FILM,LEAD-PPF	82nF,5%,400V,TP,19x15.5x7,7.5	SA
5	2301-001249	C457	C-FILM,LEAD-PPF	68nF,5%,400V,TP,19x7x15mm,7.5	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	2201-000291	C458	C-CERAMIC,DISC	1NF,10%,500V,Y5P,TP,7.5X3.5MM,5	SA
5	2401-000603	C459	C-AL	1UF,20%,50V,GP,TP,5X11,2	SA
5	2202-000654	C460	C-CERAMIC,MLC-RADIAL	100nF,10%,50V,X7R,TP,5.1x6.6x3.2mm,5	SA
5	2301-000294	C501	C-FILM,LEAD-PEF	56nF,5%,100V,TP,9.5x12.5mm,5mm	SA
5	2301-000013	C502	C-FILM,LEAD-PEF	4.7nF,5%,100V,TP,10.5x12.5x6.5	SA
5	2301-000312	C503	C-FILM,LEAD-PEF	8.2nF,5%,100V,TP,6x12.5mm,5mm	SA
5	2401-000025	C504	C-AL	100uF,20%,16V,GP,TP,6.3x11,5	SA
5	2201-000163	C505	C-CERAMIC,DISC	10NF,+80-20%,50V,Y5V,TP,7X3MM,2.5	SA
5	2305-000237	C506	C-FILM,LEAD-PEF	1uF,5%,63V,TP,7.5x15.5mm,5mm	SA
5	2202-000654	C507	C-CERAMIC,MLC-RADIAL	100nF,10%,50V,X7R,TP,5.1x6.6x3.2mm,5	SA
5	2401-000025	C508	C-AL	100uF,20%,16V,GP,TP,6.3x11,5	SA
5	2401-000025	C509	C-AL	100uF,20%,16V,GP,TP,6.3x11,5	SA
5	2305-000412	C510	C-FILM,LEAD-PEF	470nF,5%,63V,TP,-,5mm	SA
5	2303-000102	C511	C-FILM,LEAD-PEF	1.2nF,5%,1.6KV,TP,23*16*7.5,7.	SA
5	2201-000012	C512	C-CERAMIC,DISC	0.22NF,10%,1KV,Y5P,TP,6.3X5MM,5	SA
5	2401-000058	C513	C-AL	220uF,20%,100V,GP,TP,12.5x25,5	SA
5	2401-000031	C521	C-AL	47uF,20%,16V,GP,TP,5x11,5	SA
5	2202-002009	C530	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2401-000638	C531	C-AL	2.2uF,20%,350V,WT,TP,10x12.5mm	SA
5	2401-001576	C532	C-AL	47uF,20%,50V,GP,TP,8x11.5,5	SA
5	2401-002267	C533	C-AL	2.2uF,20%,250V,GP,TP,8x11.5,5	SA
5	2301-000213	C534	C-FILM,LEAD-PEF	220nF,5%,250V,TP,21.5x11,7.5	SA
5	2301-001480	C535	C-FILM,LEAD-PEF	2000NF,5%,100V,TP,17X16.5X9.5,7.5	SA
5	2401-001026	C536	C-AL	3.3UF,20%,50V,GP,TP,5X11,5	SA
5	2401-002300	C537	C-AL	47uF,20%,50V,GP,TP,6.3x11,5	SA
5	2305-000428	C541	C-FILM,LEAD-PEF	47nF,5%,250V,TP,11x9x4.5,5mm	SA
5	2401-000480	C551	C-AL	10uF,20%,50V,GP,TP,5x11,5	SA
5	2201-000129	C552	C-CERAMIC,DISC	0.1NF,10%,1KV,Y5P,TP,7X4MM,5	SA
5	2201-000285	C561	C-CERAMIC,DISC	1NF,10%,1KV,Y5P,TP,8X5MM,5	SA
5	2201-000285	C562	C-CERAMIC,DISC	1NF,10%,1KV,Y5P,TP,8X5MM,5	SA
5	2306-001011	C563	C-FILM,LEAD-PPF	56nF,5%,250V,TP,19x7.5x14.5,7.	SA
5	2301-000020	C564	C-FILM,LEAD-PEF	27nF,5%,100V,TP,7.3x4x12.5mm,5	SA
5	2301-000148	C565	C-FILM,LEAD-PEF	10nF,5%,100V,TP,7x3.2x7mm,5mm	SA
5	2201-000023	C603	C-CERAMIC,DISC	2.2NF,20%,250V,Y5U,TP,11X7MM,5	SA
5	2201-000023	C604	C-CERAMIC,DISC	2.2NF,20%,250V,Y5U,TP,11X7MM,5	SA
5	2401-000970	C606	C-AL	22uF,20%,50V,WT,TP,5x11,5	SA
5	2202-002009	C607	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2201-000325	C608	C-CERAMIC,DISC	2.2NF,10%,500V,Y5P,TP,9.5X4MM,5	SA
5	2201-000129	C609	C-CERAMIC,DISC	0.1NF,10%,1KV,Y5P,TP,7X4MM,5	SA
5	2201-000017	C610	C-CERAMIC,DISC	1NF,10%,50V,Y5P,TP,5X3.5MM,5	SA
5	2401-000611	C611	C-AL	1uF,20%,50V,WT,TP,5x11,5	SA
5	2305-000149	C613	C-FILM,LEAD-PEF	100nF,5%,100V,TP,12x12.5x6.5,5	SA
5	2301-000284	C614	C-FILM,LEAD-PEF	47nF,5%,100V,TP,8.5x12.5mm,5mm	SA
5	2401-001585	C615	C-AL	47uF,20%,50V,WT,TP,8x11.5,5	SA
5	2202-002009	C616	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2201-000023	C617	C-CERAMIC,DISC	2.2NF,20%,250V,Y5U,TP,11X7MM,5	SA
5	2401-000015	C618	C-AL	33uF,20%,50V,WT,-,6.3x11mm,2.5	SA
5	2201-000291	C619	C-CERAMIC,DISC	1NF,10%,500V,Y5P,TP,7.5X3.5MM,5	SA
5	2305-000178	C621	C-FILM,LEAD-PEF	10nF,5%,100V,TP,-,5mm	SA
5	2401-000039	C622	C-AL	1000uF,20%,16V,GP,TP,10x16,5	SA
5	2401-000025	C623	C-AL	100uF,20%,16V,GP,TP,6.3x11,5	SA
5	2401-000010	C624	C-AL	220uF,20%,16V,GP,-,6.3x11mm,2.	SA
5	2401-000010	C625	C-AL	220uF,20%,16V,GP,-,6.3x11mm,2.	SA
5	2401-000010	C626	C-AL	220uF,20%,16V,GP,-,6.3x11mm,2.	SA
5	2401-000039	C627	C-AL	1000uF,20%,16V,GP,TP,10x16,5	SA
5	2401-000058	C628	C-AL	220uF,20%,100V,GP,TP,12.5x25,5	SA
5	2401-003826	C629	C-AL	220UF,20%,63V,LR,TP,10X25MM,5	SA
5	2201-000732	C630	C-CERAMIC,DISC	0.68NF,10%,1KV,Y5P,TP,7X4MM,5	SA
5	2401-000039	C631	C-AL	1000uF,20%,16V,GP,TP,10x16,5	SA
5	2401-000058	C633	C-AL	220uF,20%,100V,GP,TP,12.5x25,5	SA
5	2201-000017	C634	C-CERAMIC,DISC	1NF,10%,50V,Y5P,TP,5X3.5MM,5	SA
5	0203-001600	CIS10	TAPE-PAPER	#53128,0.15,5.5,2000M,BEIGE	SNA
5	0203-001599	CIS9	TAPE-KRAFT	#53110,0.1,6,2000M,BRN	SNA
5	BH71-40300A	CN420	PIN-HINGE	BRASS,D2.36!,HEAT/SINK,SN	SNA
5	BH71-40300A	CN421	PIN-HINGE	BRASS,D2.36!,HEAT/SINK,SN	SNA
5	3711-000217	CN602	CONNECTOR-HEADER	1WALL,2P,1R,7.92MM,STRAIGHT,SN,NTR	SA
5	0401-000005	D201	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D251	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D252	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	0402-000274	D301	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0401-000005	D401	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D402	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0402-001118	D411	DIODE-RECTIFIER	UF1G,400V,1.2A,DO-204AC,TP	SA
5	0402-000274	D412	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0401-000004	D441	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0402-000274	D451	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0401-000005	D501	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D502	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D504	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D506	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D508	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D509	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0402-000274	D510	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0402-000012	D531	DIODE-RECTIFIER	UF4007,1KV,1A,DO-41,TP	SA
5	0402-000274	D532	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0402-000017	D533	DIODE-RECTIFIER	RGP02-12,1.2KV,0.5A,DO-204AL,TP	SA
5	0401-000005	D541	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0402-001114	D542	DIODE-RECTIFIER	1N4936GP,400V,1A,DO-201AD,TP	SA
5	0402-000546	D543	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41,TP	SA
5	0401-000005	D544	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D551	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0402-000012	D603	DIODE-RECTIFIER	UF4007,1KV,1A,DO-41,TP	SA
5	0402-000012	D604	DIODE-RECTIFIER	UF4007,1KV,1A,DO-41,TP	SA
5	0402-000546	D605	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41,TP	SA
5	0402-000546	D606	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41,TP	SA
5	0401-000005	D607	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D608	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D621	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0402-001194	D622	DIODE-RECTIFIER	UG2D,200V,2A,-,TP	SA
5	0402-000274	D623	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0402-000274	D624	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0402-001194	D627	DIODE-RECTIFIER	UG2D,200V,2A,-,TP	SA
5	0402-001118	D628	DIODE-RECTIFIER	UF1G,400V,1.2A,DO-204AC,TP	SA
5	6042-000001	EY301	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY302	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY401	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY402	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY403	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY404	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY405	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY411	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY415	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY422	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY423	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY454	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY455	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY501	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY502	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY503	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY504	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY505	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY506	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY507	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY601	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY602	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY603	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY604	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY605	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY606	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY607	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY608	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY621	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY622	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY623	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	BH71-40300A	GT401	PIN-HINGE	BRASS,D2.36!,HEAT/SINK,SN	SNA
5	BH71-40300A	GT402	PIN-HINGE	BRASS,D2.36!,HEAT/SINK,SN	SNA
5	BH71-40300A	GT601	PIN-HINGE	BRASS,D2.36!,HEAT/SINK,SN	SNA
5	BH71-40300A	GT602	PIN-HINGE	BRASS,D2.36!,HEAT/SINK,SN	SNA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	1103-001150	IC241	IC-EEPROM	24C081,1Kx8,DIP,8P,9.2x6.4mm,2.7/5.5V,-25to+70C	SA
5	1203-000610	IC501	IC-PWM CONTROLLER	494,DIP,16P,300MIL,PLASTIC,40V,1W,0TO+70C,250MA,4.75/5.25V,ST	SA
5	BH39-40305U	JP_DHH	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP1	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP10	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP11	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP12	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP13	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP14	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP15	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP16	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP17	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP18	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP19	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP20	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP21	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP22	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP23	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP24	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP25	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP26	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP27	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP28	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP29	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP3	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP30	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP31	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP32	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP33	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP34	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP35	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP36	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP37	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP38	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP39	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP4	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP40	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP41	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP42	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP43	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP44	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP45	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP46	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP47	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP48	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP49	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP5	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP50	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP51	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP52	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP53	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP54	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP57	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP58	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP60	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP61	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP62	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP63	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP64	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP65	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP66	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP67	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP68	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP69	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP7	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP70	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP71	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP72	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP73	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	BH39-40305U	JP74	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP75	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP76	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP77	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP78	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP79	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP8	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP80	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP82	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP83	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP9	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	2701-000189	L218	INDUCTOR-AXIAL	0.47UH,10%,2534	SA
5	2701-000116	L501	INDUCTOR-AXIAL	10UH,10%,4298	SA
5	BH41-00270A	MP1.0	PCB MAIN	LE19IS,FR-1,1,1.0,1.6T,247*247,LE19,MAIN	SNA
5	0501-000122	Q321	TR-SMALL SIGNAL	2N3904,NPN,625mW,TO-92,TP,100-300	SA
5	0501-000581	Q322	TR-SMALL SIGNAL	2N3906,PNP,625mW,TO-92,TP,100-300	SA
5	0501-000586	Q323	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000586	Q403	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000303	Q404	TR-SMALL SIGNAL	KSA733,PNP,250mW,TO-92,TP,120-240	SA
5	0501-000586	Q411	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000303	Q412	TR-SMALL SIGNAL	KSA733,PNP,250mW,TO-92,TP,120-240	SA
5	0501-000586	Q455	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000586	Q456	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000586	Q457	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000586	Q458	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000404	Q459	TR-SMALL SIGNAL	KSD1616-Y,NPN,750mW,TO-92,TP,135-270	SA
5	0501-000122	Q502	TR-SMALL SIGNAL	2N3904,NPN,625mW,TO-92,TP,100-300	SA
5	0501-000581	Q503	TR-SMALL SIGNAL	2N3906,PNP,625mW,TO-92,TP,100-300	SA
5	0501-000122	Q523	TR-SMALL SIGNAL	2N3904,NPN,625mW,TO-92,TP,100-300	SA
5	0501-000586	Q541	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000143	Q542	TR-SMALL SIGNAL	2N6520,PNP,625mW,TO-92,TP,30-200	SA
5	0501-000413	Q551	TR-SMALL SIGNAL	KSP44,NPN,625mW,TO-92,TP,50-200	SA
5	0501-000122	Q601	TR-SMALL SIGNAL	2N3904,NPN,625mW,TO-92,TP,100-300	SA
5	0501-000404	Q604	TR-SMALL SIGNAL	KSD1616-Y,NPN,750mW,TO-92,TP,135-270	SA
5	0501-000010	Q621	TR-SMALL SIGNAL	KSC1008,NPN,800mW,TO-92,TP,120-240	SA
5	0501-000586	Q622	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000586	Q624	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000321	Q625	TR-SMALL SIGNAL	KSB1116-Y,PNP,750mW,TO-92,TP,135-270	SA
5	2001-000429	R201	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R202	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R203	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R204	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R205	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R206	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000800	R207	R-CARBON	5.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000739	R208	R-CARBON	4.7MOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R209	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R210	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R211	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R212	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R213	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R214	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R215	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000006	R216	R-CARBON	2.4KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000006	R217	R-CARBON	2.4KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000793	R218	R-CARBON	47OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R219	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R220	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R221	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R222	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R223	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R224	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R227	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000435	R228	R-CARBON	1MOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000435	R229	R-CARBON	1MOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R230	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000554	R231	R-CARBON	270OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000869	R232	R-CARBON	56OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000869	R233	R-CARBON	56OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	2001-000281	R234	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R235	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R236	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R241	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R242	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R243	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R244	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000977	R301	R-CARBON	8.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2004-000216	R302	R-METAL	10Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2004-000616	R304	R-METAL	24Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2001-001078	R305	R-CARBON(S)	15KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2004-001005	R306	R-METAL	5.1Kohm,1%,1/4W,AA,TP,2.4x6.4m	SA
5	2004-004038	R307	R-METAL	4.3Kohm,1%,1/4W,AA,TP,2.4x6.4m	SA
5	2004-004231	R308	R-METAL(S)	2.4OHM,1%,1/2W,AA,TP,3.3X9MM	SA
5	2004-001391	R309	R-METAL(S)	2.2ohm,1%,1/2W,AA,TP,2.4x6.4mm	SA
5	2001-000037	R310	R-CARBON(S)	330OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000290	R311	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001053	R312	R-CARBON(S)	1.5OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000977	R313	R-CARBON	8.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R321	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000331	R322	R-CARBON	12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000302	R323	R-CARBON	10OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000864	R324	R-CARBON	56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000042	R325	R-CARBON	1KOHM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000281	R326	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001079	R327	R-CARBON(S)	15OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-001079	R328	R-CARBON(S)	15OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000319	R401	R-CARBON	120KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000221	R402	R-CARBON	1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000221	R403	R-CARBON	1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000490	R404	R-CARBON	200OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000739	R405	R-CARBON	4.7MOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000052	R406	R-CARBON(S)	3.3KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-001078	R407	R-CARBON(S)	15KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2003-000608	R408	R-METAL OXIDE(S)	270ohm,5%,3W,AA,TP,6x16mm	SA
5	2003-000763	R410	R-METAL OXIDE(S)	6.8ohm,5%,3W,AA,TP,6x16mm	SA
5	2003-000468	R411	R-METAL OXIDE(S)	10ohm,5%,1W,AA,TP,3.3x9mm	SA
5	2001-000008	R412	R-CARBON	15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2003-000005	R413	R-METAL OXIDE(S)	1ohm,5%,2W,AA,TP,4x12mm	SA
5	2001-000107	R415	R-CARBON(S)	150KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2004-001118	R431	R-METAL	5Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2001-000449	R432	R-CARBON	2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2004-004367	R433	R-METAL	90Kohm,1%,1/4W,AA,TP,6.2x2.6mm	SA
5	2001-000449	R434	R-CARBON	2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000010	R435	R-CARBON	68KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000356	R436	R-CARBON	150KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2004-001230	R437	R-METAL	75Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2004-000657	R438	R-METAL	27Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2004-000412	R439	R-METAL	18Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2001-000890	R440	R-CARBON	6.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000577	R441	R-CARBON	2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000563	R442	R-CARBON	27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R451	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R452	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R453	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R454	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000411	R455	R-CARBON	18KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000411	R456	R-CARBON	18KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000411	R457	R-CARBON	18KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000411	R458	R-CARBON	18KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R459	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R460	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R461	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R462	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2003-000450	R463	R-METAL OXIDE(S)	100Kohm,5%,3W,AA,TP,6x16mm	SA
5	2003-000541	R464	R-METAL OXIDE(S)	1Kohm,5%,3W,AA,TP,6x16mm	SA
5	2003-000671	R465	R-METAL OXIDE(S)	390ohm,5%,2W,AA,TP,4x12mm	SA
5	2001-000290	R467	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2003-000514	R468	R-METAL OXIDE(S)	15ohm,5%,2W,AA,TP,4x12mm	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	BH39-40305U	R469	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	2001-000241	R501	R-CARBON	1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R502	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000812	R503	R-CARBON	5.6KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000689	R504	R-CARBON	390KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000786	R505	R-CARBON	47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R506	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000331	R507	R-CARBON	12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R509	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000241	R510	R-CARBON	1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001153	R511	R-CARBON(S)	47OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-001144	R512	R-CARBON(S)	4.7KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2005-001172	R513	R-WIRE WOUND,NON	0.6ohm,5%,3W,AA,TP,5.5x15mm	SA
5	2003-000432	R515	R-METAL OXIDE(S)	1.5Kohm,5%,3W,AA,TP,6x16mm	SA
5	2004-001005	R516	R-METAL	5.1Kohm,1%,1/4W,AA,TP,2.4x6.4m	⚠ SA
5	2001-000878	R520	R-CARBON	6.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000800	R521	R-CARBON	5.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2004-001136	R522	R-METAL	6.8Kohm,1%,1/4W,AA,TP,2.4x6.4m	SA
5	2001-000734	R523	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2004-001298	R526	R-METAL	82Kohm,2%,1/4W,AA,TP,2.4x6.4mm	⚠ SA
5	2001-000429	R530	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000073	R531	R-CARBON	33KOHM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2004-000781	R532	R-METAL	330Kohm,1%,1/4W,AA,TP,2.4x6.4m	⚠ SA
5	2004-000560	R533	R-METAL	220Kohm,1%,1/4W,AA,TP,2.4x6.4m	⚠ SA
5	2001-000800	R534	R-CARBON	5.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2004-000252	R535	R-METAL	11Kohm,1%,1/4W,AA,TP,2.4x6.4mm	⚠ SA
5	2001-000591	R541	R-CARBON	3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R542	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2002-001091	R543	R-COMPOSITION	270KOHM,5%,1/2W,AA,TP,3X9MM	SA
5	2002-001062	R544	R-COMPOSITION	150Kohm,2%,1/2W,AA,TP,3.9x9mm	SA
5	2002-000121	R545	R-COMPOSITION	1Mohm,10%,1/2W,AA,TP,3.5x9.5mm	SA
5	2001-000734	R550	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R551	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000331	R553	R-CARBON	12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R554	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R555	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2002-001079	R556	R-COMPOSITION	470Kohm,5%,1/2W,AA,TP,4x10mm	SA
5	2002-001079	R557	R-COMPOSITION	470Kohm,5%,1/2W,AA,TP,4x10mm	SA
5	2001-000114	R558	R-CARBON(S)	180KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000114	R559	R-CARBON(S)	180KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2003-000514	R561	R-METAL OXIDE(S)	15ohm,5%,2W,AA,TP,4x12mm	SA
5	2001-000221	R562	R-CARBON	1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001129	R601	R-CARBON(S)	330KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-001129	R602	R-CARBON(S)	330KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2003-000738	R603	R-METAL OXIDE(S)	56Kohm,5%,2W,AA,TP,4x12mm	SA
5	2003-000014	R604	R-METAL OXIDE(S)	10Kohm,5%,3W,AA,TP,6x16mm	SA
5	2002-001103	R605	R-COMPOSITION	300Kohm,5%,1/2W,AA,TP,3.7x10.0mm	SA
5	2002-001103	R606	R-COMPOSITION	300Kohm,5%,1/2W,AA,TP,3.7x10.0mm	SA
5	2001-001116	R607	R-CARBON(S)	27OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000734	R608	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000780	R609	R-CARBON	470OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R610	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	BH39-40305U	R611	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	2001-000023	R621	R-CARBON	47OHM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000027	R622	R-CARBON	100OHM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000613	R623	R-CARBON	3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000857	R624	R-CARBON	560OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R626	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R627	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000472	R628	R-CARBON	2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000786	R629	R-CARBON	47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2003-000473	R631	R-METAL OXIDE(S)	10ohm,5%,3W,AA,TP,6x16mm	SA
5	2001-001108	R632	R-CARBON(S)	22KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000613	R634	R-CARBON	3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	4715-001055	SK531	SURGE ABSORBER	1kV,+50-10%,-,-,RADIAL	SNA
5	6042-000002	TP501	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	2801-000006	X201	CRYSTAL-UNIT	12MHz,50ppm,28-AAM,S,35ohm,BK	SA
5	0403-000337	ZD201	DIODE-ZENER	UZ24BH,24.26-25.52V,500MW,DO-35,TP	SA
5	0403-001068	ZD202	DIODE-ZENER	UZ4.7BSA,4.44-4.68V,500MW,DO-34,TP	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	0403-000361	ZD221	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD222	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD223	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD224	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD225	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD501	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-001167	ZD541	DIODE-ZENER	MTZJ30D,29.02-30.51V,500MW,DO-34,TP	SA
5	0403-001221	ZD542	DIODE-ZENER	UZ39BSB,35.36-37.19V,500MW,DO-34,TP	SA
5	0403-001068	ZD543	DIODE-ZENER	UZ4.7BSA,4.44-4.68V,500MW,DO-34,TP	SA
5	0403-001221	ZD601	DIODE-ZENER	UZ39BSB,35.36-37.19V,500MW,DO-34,TP	SA
5	0403-000361	ZD602	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
4	BH99-00030F	HS422	ASSY HEAT/SINK	HS TR,SCREW+NUT,IRFS630B(4),OIL SILICON	SNA
5	0205-001154	CIS	OIL-SILICON	G746,-,-	SNA
5	0505-001716	CIS	FET-SILICON	IRFS630B,N,200V,9A,0.4OHM,38W,TO-220F	SA
5	6006-001008	CIS	SCREW-ASS'Y MACH	WSP,BH,+,M3,L10,ZPC(YEL),SWRCH	SNA
5	6021-000118	CIS	NUT-HEXAGON	1C,M3,ZPC(YEL),SM20C	SNA
5	BH62-00044A	CIS	HEAT SINK-TR	AQ19FS,A1050S,T2.0,20,55,-,-,-	SNA
4	BH99-10019H	HS411	ASSY HEAT/SINK	H/S TR,SCREW+NUT,IRF634A,-,-,OIL SILICON,-,-	SNA
5	0205-001154	CIS	OIL-SILICON	G746,-,-	SNA
5	0505-001181	CIS	FET-SILICON	IRF634A,N,250V,8.1A,450mohm,74	SA
5	6006-001008	CIS	SCREW-ASS'Y MACH	WSP,BH,+,M3,L10,ZPC(YEL),SWRCH	SNA
5	6021-000118	CIS	NUT-HEXAGON	1C,M3,ZPC(YEL),SM20C	SNA
5	BH62-30024B	CIS	HEAT SINK-IC	SPC-1,T1,SN COATING,-	SNA
4	BN61-01137A	CIS16	SUPPORT-CLIP	IBM E74,NYLON 66,1.0,NTR	SNA
4	BP96-00065B	HS301	ASSY HEAT SINK P	BH62-00003B,SCREW,STV9325,OIL SILICON	SNA
5	0205-001154	H/S	OIL-SILICON	G746,-,-	SNA
5	1204-002262	H/S	IC-VERTICAL DEF.	STV9325,HEPTAWATT,7P,15.45x10.22mm,PLASTIC,35V,-,-40to+150C,ST,IC-VERTICAL DEF.	SNA
5	6003-000334	H/S	SCREW-TAPTITE	RH,+,2S,M3,L6,ZPC(YEL),SWRCH18	SNA
5	BH62-00003B	H/S	HEAT SINK-VERT	A1050S,T1.0,T1.0,-,DA,DB	SNA
4	BP96-00075D	HS601	ASSY HEAT SINK P	BH62-00052A,SPRING,8SA0965,SILICON RUBBER	SNA
5	BH13-00049A	H/S	IC HYBRID	FS8S0965RCB(DP906C),LE19IS,5,-25 to 85,TO-220(FORMING),35,ST	SA
5	BH61-00004A	H/S	SPRING ETC-TR	CDA,CDB,SUS304,-,-,-,-,-,T0.5,-,-,-	SNA
5	BH62-00052A	H/S	HEAT SINK-POWER	M782,A1050S,T1.0,W25,L55,-,BH62,-	SNA
5	BH62-20001B	H/S	TUBE-RUBBER	CSQ4357,W25*L20*T0.45,-,-,-,-	SNA

7-3-2 LE19IT Video PCB Parts

Level	Loc. No.	Code No.	Description	Specification	Remarks
3	BH94-00978A	-	ASSY PCB VIDEO-ST	LE19IS	SNA
4	6003-001023	-	SCREW-TAPTITE	RWH,+,B,M3,L10,ZPC(YEL),SWRCH1	SNA
4	BH39-00386A	CIS	CBF-GROUND ASS'Y	MS17J0,8*0.16*16TA,1P/2P,80MM,35750-1010,EARTH PLATE CLIP,BK,8*0.16*16TA	SA
4	BH63-00131A	CIS1	SHIELD-VIDEO	LE17KS,SPTE,T0.2	SNA
4	0204-002426	CIS3	FLUX	DF-201TVS,MIX,0.820,FLUX13%,14KG,-	SNA
4	0204-002420	CIS4	SOLVENT	1M-1000,C3H70H,96,-,-	SNA
4	BH68-00001A	CIS40	LABEL-MARK CDT	ART-PAPER100G,-,WHT,BLK,-,ALL,CDT	SNA
4	3711-004236	CN101	CONNECTOR-HEADER	BOX,6P,1R,2MM,STRAIGHT,SN	SNA
4	BH39-00015A	CN102	CBF-HARNESS	13P/14P,200MM,WHT/BLK/RED/BLU,UL1007,AWG26,SMH200-13/YBNH200-14	SA
4	BH13-00050A	IC102	IC HYBRID	NT6813K-30031,NT6813K-30031,24P,-55 to +150,240mA,-0.5 to 6V,ST	SA
4	3704-001203	SK101	SOCKET-CRT	9P,29PI,22.5PI,NI+SN,-	SNA
4	BH96-00283B	HS106	ASSY HEAT SINK P	BH62-00054A,SCREW,LM2463,OIL SILICON	SNA
5	0205-001154	H/S	OIL-SILICON	G746,-,-	SNA
5	1201-002116	H/S	IC-VIDEO AMP	LM2463,TO-220,11P,17.5x20.01mm,-,-20,PLASTIC,100V,-,0to70C,-,-,-,-,-,ST	SA
5	6003-000334	H/S	SCREW-TAPTITE	RH,+,2S,M3,L6,ZPC(YEL),SWRCH18	SNA
5	BH62-00054A	H/S	HEAT SINK-PS	LEO,A1050S,2.0,112,25	SNA

Level	Loc. No.	Code No.	Description	Specification	Remarks
4	BH97-00510A	-	ASSY AUTO-(VIDEO)ST	LE19IS	SNA
5	3301-001450	BD101	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD102	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD104	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001660	BD105	BEAD-RADIAL	100OHM,3.5X9.0X0.8,50MA,TP,K-150,00HM	SA
5	3301-001450	BD106	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	2202-002009	C101	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2401-000025	C103	C-AL	100uF,20%,16V,GP,TP,6.3x11,5	SA
5	2401-000603	C104	C-AL	1UF,20%,50V,GP,TP,5X11,2	SA
5	2201-000019	C106	C-CERAMIC,DISC	10nF,+80-20%,500V,Y5V,TP,13.5x4mm,5	SA
5	2401-003036	C111	C-AL	100uF,20%,16V,GP,TP,5X11mm,5mm	SA
5	2202-002009	C112	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2401-003036	C113	C-AL	100uF,20%,16V,GP,TP,5X11mm,5mm	SA
5	2201-000119	C114	C-CERAMIC,DISC	100NF,+80-20%,50V,Y5V,TP,8X3MM,5	SA
5	2401-003036	C115	C-AL	100uF,20%,16V,GP,TP,5X11mm,5mm	SA
5	2202-002009	C116	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2301-000148	C117	C-FILM,LEAD-PEF	10nF,5%,100V,TP,7x3.2x7mm,5mm	SA
5	2201-000483	C118	C-CERAMIC,DISC	0.033NF,5%,50V,C0G,TP,5X3.5MM,5	SA
5	2401-003036	C119	C-AL	100uF,20%,16V,GP,TP,5X11mm,5mm	SA
5	2202-002009	C120	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2401-003036	C121	C-AL	100uF,20%,16V,GP,TP,5X11mm,5mm	SA
5	2202-002009	C122	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2301-000010	C123	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2401-000049	C124	C-AL	47uF,20%,100V,WT,TP,10x16,5	SA
5	2202-002009	C125	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2201-000119	C126	C-CERAMIC,DISC	100NF,+80-20%,50V,Y5V,TP,8X3MM,5	SA
5	2201-000119	C131	C-CERAMIC,DISC	100NF,+80-20%,50V,Y5V,TP,8X3MM,5	SA
5	2201-000019	C132	C-CERAMIC,DISC	10nF,+80-20%,500V,Y5V,TP,13.5x4mm,5	SA
5	2201-000154	C133	C-CERAMIC,DISC	10NF,+80-20%,2KV,Y5P,TP,20X5MM,7.5	SA
5	2202-000286	C134	C-CERAMIC,MLC-AXIAL	56pF,5%,50V,SL,TP,1.9x3.5,-	SA
5	2202-000286	C135	C-CERAMIC,MLC-AXIAL	56pF,5%,50V,SL,TP,1.9x3.5,-	SA
5	2202-002009	CB01	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2202-002009	CB02	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2301-000010	CB03	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2401-003911	CB04	C-AL	1uF,20%,160V,BP,TP,6.3x11mm,5	SA
5	2202-002009	CG01	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2202-002009	CG02	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2301-000010	CG03	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2401-003911	CG04	C-AL	1uF,20%,160V,BP,TP,6.3x11mm,5	SA
5	6502-000001	CIS	CABLE CLAMP	DAWH-5NB,D15,L35,NYLON66,NTR	SNA
5	0203-001599	CIS6	TAPE-KRAFT	#53110,0.1,6,2000M,BRN	SNA
5	0203-001600	CIS7	TAPE-PAPER	#53128,0.15,5.5,2000M,BEIGE	SNA
5	BH71-40300A	CN_G2	PIN-HINGE	BRASS,D2.36!,HEAT/SINK,SN	SNA
5	BH71-40300A	CN_GND	PIN-HINGE	BRASS,D2.36!,HEAT/SINK,SN	SNA
5	2202-002009	CR01	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2202-002009	CR02	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2301-000010	CR03	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2401-003911	CR04	C-AL	1uF,20%,160V,BP,TP,6.3x11mm,5	SA
5	0401-000005	DB01	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	DB02	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000004	DB03	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DB04	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DB05	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000005	DG01	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	DG02	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000004	DG03	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DG04	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DG05	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000005	DR01	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	DR02	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000004	DR03	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DR04	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DR05	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	6042-000001	EY1	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY2	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY3	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY4	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY5	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	BH13-00022A	IC104	IC HYBRID-BIAS CLAMP	LM2480NA,PN15H/17L,8P,0to+70C,DIP,3mA,85V,ST	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	BH39-40305U	JP101	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP102	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP103	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP104	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP105	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	2701-001062	LB01	INDUCTOR-AXIAL	0.12UH,10%,3070	SA
5	2701-001092	LB02	INDUCTOR-AXIAL	0.07uH,10%,2360	SA
5	2701-001062	LG01	INDUCTOR-AXIAL	0.12UH,10%,3070	SA
5	2701-001092	LG02	INDUCTOR-AXIAL	0.07uH,10%,2360	SA
5	2701-001062	LR01	INDUCTOR-AXIAL	0.12UH,10%,3070	SA
5	2701-001092	LR02	INDUCTOR-AXIAL	0.07uH,10%,2360	SA
5	BH41-00271A	MP1.0	PCB-VIDEO	LE19IS,FR-1,1,1.0,1.6T,82.3*123.5,LE19,6,VIDEO	SNA
5	2001-000577	R102	R-CARBON	2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R103	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R105	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R106	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000016	R107	R-CARBON(S)	1OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000435	R111	R-CARBON	1MOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000812	R112	R-CARBON	5.6KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R113	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R114	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001138	R131	R-CARBON(S)	390OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000037	R132	R-CARBON(S)	330OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000947	R134	R-CARBON	7.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000084	R135	R-CARBON	100Kohm,5%,1/4W,AA,TP,2.4x6.4mm	SA
5	2001-000969	RB01	R-CARBON	75OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000969	RB02	R-CARBON	75OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	RB03	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001187	RB05	R-CARBON(S)	75OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000429	RB06	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001129	RB07	R-CARBON(S)	330KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000022	RB08	R-CARBON(S)	33OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000969	RG01	R-CARBON	75OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000969	RG02	R-CARBON	75OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	RG03	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001199	RG05	R-CARBON(S)	91OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000429	RG06	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001129	RG07	R-CARBON(S)	330KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000022	RG08	R-CARBON(S)	33OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000969	RR01	R-CARBON	75OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000969	RR02	R-CARBON	75OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	RR03	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001187	RR05	R-CARBON(S)	75OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000429	RR06	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001129	RR07	R-CARBON(S)	330KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000022	RR08	R-CARBON(S)	33OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	1405-001064	SK104	SURGE ABSORBER	400V,20%,-,-,AXIAL	SA
5	4715-001065	SK105	SURGE ABSORBER	200V,20%,-,-,RADIAL	SNA
5	4715-001055	SK108	SURGE ABSORBER	1kV,+50-10%,-,-,RADIAL	SNA
5	4715-001065	SKB01	SURGE ABSORBER	200V,20%,-,-,RADIAL	SNA
5	4715-000102	SKG01	SURGE ABSORBER	200V,20%,1000A,-,RADIAL	SNA
5	4715-000102	SKR01	SURGE ABSORBER	200V,20%,1000A,-,RADIAL	SNA
5	0403-001068	ZD105	DIODE-ZENER	UZ4.7BSA,4.44-4.68V,500MW,DO-34,TP	SA

7-3-3 LE19IT Others

Level	Loc. No.	Code No.	Description	Specification	Remarks
2	BH90-00605B	-	ASSY COVER FRONT	LE19IT,EDC	SNA
3	6003-000009	C/F+C/R	SCREW-TAPTITE	BH,+,B,M4,L16,ZPC(YEL),SWRCH18	SNA
3	6006-001119	C/F+CDT	SCREW-ASS'Y TAPT	WC,BH,+,M5,L25,ZPC(YEL),SWRCH18A	SNA

Level	Loc. No.	Code No.	Description	Specification	Remarks
3	BH96-00279A	C/F	ASSY COVER P-FRONT	LE19IT,ABS HB IV16	SNA
2	BH90-00617B	-	ASSY COVER REAR	LE19IT,EDC	SNA
3	BH63-00137C	C/R	COVER-REAR	LE19IT,ABS HB IV16,SAMTRON	SNA
2	BH90-00628A	-	ASSY STAND	LE19IS,EDC	SNA
3	BH96-00273A	STD	ASSY STAND P	LE19IS,ABS HB IV16	SNA
2	BH91-00843N	-	ASSY CDT-ST	LE19IS	SNA
3	0203-000005	CDT	TAPE-ACETATE	SGT730,T0.26,W19,L3000,BLK	SNA
3	0204-002421	CDT	COMPOUND	KS650N,-,0.9-1.1,1L,20L,-	SNA
3	3302-000006	CDT	MAGNET-RUBBER	AF,14G,1620-1980G,0.58-0.9MGOe	SA
3	3309-000002	CDT	MAGNET-SHEET	5x20x80mm,UL94V-0,2	SA
3	BH03-00047U	CDT	CDT-ST	M46QCK761X216(T4),84,19,0.25,29.1,IFT,H/C,NH,TCO,TILT,4	SA
3	BH68-30003C	CDT	LABEL-00,HIGH,VOLTAGE	SS,ART100G,30*33,YEL	SNA
3	BH96-00294A	CDT	ASSY D-COIL P	19 inch,BH27-00147A,BH96-00288A	SNA
2	BH91-00884A	-	ASSY SHIELD	LE19IS	SNA
3	0201-001059	CIS	ADHESIVE-SIL	#9590,WHT,-,CARTRIGE	SNA
3	6003-000010	SH/COV+SH/BTM	SCREW-TAPTITE	BWH,+,B,M3,L10,ZPC(YEL),SWRCH1	SA
3	BH96-00280A	CIS	ASSY MISC P-SHIELD COVER	LE19IS,SECC T0.5,AL T0.25	SNA
2	BH91-00919A	-	ASSY CHASSIS-ST	LE19IS,EDC	SA
2	BH92-01068A	-	ASSY P/MATERIAL	LE19IS	SNA
3	0203-001102	P/M	TAPE-OPP MASKING	OPP-2,T0.05,W100,L400M,CLR	SNA
3	6902-000001	P/M	BAG AIR	LDPE,T0.2,L1800,W1000,TRP,,,LDPE ONLY	SNA
3	6902-000108	P/M	BAG PE	HDPE,T0.015,L1100,W1120,TRP,28,4,PE MARK	SNA
3	6902-000379	P/M	BAG AIR	HDPE,T0.2,L1800,W1000,TRP,,,PAPER	SNA
3	6902-000609	P/M	BAG ROLL	LDPE,T0.05,W2400,L1000,TRP,-,-	SNA
3	BH69-00565A	P/M	CUSHION	LE19IS,EPS M50,DF	SNA
3	BH69-40380A	P/M	PACKING-PAD	DW-2,500X2200X200,-,CGK5527	SNA
2	BH92-01074B	-	ASSY BOX	LE19IT,EDC	SNA
3	BH68-00530A	BOX	LABEL BOX-01	LABEL-BARCODE,CE+TCO03,MOJO 90G,WHT	SNA
3	BH69-00579A	BOX	BOX-00,MONITOR	S/T98PDF(LE19IT) W/W,CB-DW3,YEL,A-1,W542*D592*H477	SNA
2	BH92-01093A	-	ASSY LABEL	LEO-PJT(15/17/19)	SNA
3	BH68-00565A	LABEL	LABEL RATING-00	ALL,SS,PE,T0.05,90*65,BLK,POLYESTER,NO SILK	SNA
2	BH92-01162D	-	ASSY ACCESSORY	LEO	SNA
3	BH96-00297D	UNIT/ACCESSORY	ASSY ACCESSORY	LEO	SNA
4	0203-000214	ACCESSORY	TAPE-OPP MASKING	OPP/W50/CLR,T0.05,W50,L400000,	SNA
4	6902-000110	ACCESSORY	BAG PE	LDPE,T0.05,L356,W240,TRP,28,2,PE MARK	SNA
4	BH39-10339H	ACCESSORY	CBF POWER CORD	DET,H05VV-F,250V/10,16A,BLK,25	SA
4	BH68-70420A	ACCESSORY	CARD-EU WARRNTY-05	SAMTRON15 OVER,SAMTRON,EU,MOJ	SNA
4	BH96-00296B	ACCESSORY	ASSY MANUAL P-IB+QSG	78E,78DF,78BDF,98PDF,SAMTRON,W/W,27Lang,BH59-362B+BH68-376J	SNA
5	BH59-00362B	I/B	S/W DRIVER-00,IB	591S,78E,78BDF,98PDF,W/W,SAMTRON,27LANG	SNA
5	BH68-00376J	I/B	MANUAL-01	AN_QUICK SETUP GUIDE,SYNCMASTER,E/F/S/G/P/I..14LANGS,W/W,MOJO100G,298,420	SNA